

**LIBERTY**

**Requirements For  
Electric Service and Meter Installations**

# **Residential**



**Liberty™**

**(800) 206 – 2300**

The latest revision of this book can be found on-line at:  
<https://central.libertyutilities.com/all/residential/new-service/service-standards.html>  
Select "Residential Service Standards 2025"

Effective 01/01/2025 (REVO)



Some of the information in this booklet is based on governmental codes and ordinances as well as the National Electric Safety Code, National Electrical Code, and Liberty tariffs on file with the Public Service Commissions. These requirements and guidelines are issued with the intent of complying with all applicable codes, ordinances and tariffs. In the case of conflict, the appropriate code, ordinance, and tariff will supersede the interpretation offered in this booklet. In addition, these requirements are subject to change in the event that the governing codes, ordinances and tariffs are changed. Liberty does not assume responsibility for keeping this book current and should be consulted in case of doubt on the applicability of any terms.

When the term "contact the Company" is used in this booklet, it shall mean for each and every installation, not a single contact.

This publication includes a number of changes and supersedes all previous editions.

**THIS PAGE INTENTIONALLY LEFT BLANK**

# TABLE OF CONTENTS

<b>1.0 INTRODUCTION</b>	<b>1</b>
<b>2.0 GENERAL INFORMATION</b>	<b>2</b>
2.1 <i>DEFINITIONS</i>	2
2.2 <i>AVAILABILITY AND LOCATION OF SERVICE</i>	7
2.3 <i>TYPE AND CHARACTER OF SERVICE</i>	7
2.4 <i>GENERAL REQUIREMENTS</i>	8
<b>2.5 ALTERATIONS AND ADDITIONS</b>	<b>8</b>
<b>3.0 METERING</b>	<b>9</b>
3.1 <i>GROUNDING</i>	9
3.2 <i>METERING EQUIPMENT LOCATIONS</i>	9
<b>4.0 INFORMATION APPLYING TO ALL SERVICES</b>	<b>10</b>
<b>5.0 TEMPORARY SERVICES</b>	<b>11</b>
<b>6.0 OVERHEAD SERVICES</b>	<b>16</b>
6.1 <i>GENERAL INFORMATION</i>	16
6.2 <i>100 AMP, 200 AMP, AND 320 AMP SINGLE PHASE OVERHEAD SERVICES</i>	18
6.3 <i>MULTIPLE METERS, SINGLE PHASE OVERHEAD SERVICE</i>	34
<b>7.0 UNDERGROUND SERVICES</b>	<b>38</b>
7.1 <i>GENERAL INFORMATION</i>	38
7.2 <i>200 AMP AND 320 AMP SINGLE PHASE UNDERGROUND SERVICE</i>	43
7.3 <i>600 AMP TO 800 AMP CT METERING, SINGLE PHASE UNDERGROUND SERVICE</i>	55
7.4 <i>MULTIPLE METERS, SINGLE PHASE UNDERGROUND SERVICE</i>	59
<b>Appendix A</b>	<b>65</b>
<b>Appendix B</b>	<b>72</b>

# TABLE OF FIGURES

Figure 1: Definitions.....	4
Figure 2: Definitions.....	5
Figure 3: Definitions.....	6
Figure 4: Temporary Service from Overhead Facilities .....	12
Figure 5: Temporary Service from Underground Facilities .....	13
Figure 6: Temporary Service from Underground Facilities (Continued).....	14
Figure 8: 100/200/320 Amp Overhead Service.....	20
Figure 9: 100/200/320 Amp Steel Service Mast .....	21
Figure 10: 100/200 Amp Meter Socket, Overhead Service .....	22
Figure 11: 100/200 Amp Meter Socket, Network (120/208), Overhead Service .....	23
Figure 12: 100/200 Amp Combination Meter Socket.....	24
Figure 13: 100/200 Amp Combination Meter Socket, Network (120/208), Overhead Service .....	25
Figure 14: 320 Amp Meter Socket, Overhead Service .....	26
Figure 14A: 320 Amp Meter Socket, Network (120/208), Overhead Service.....	27
Figure 15: 320 Amp Combination Meter Socket, Overhead Service .....	28
Figure 15A: 320 Amp Combination Meter Socket, Network (120/208), Overhead Service.....	29
Figure 16: 100/200 Amp Meter Pole, Underground Feeder .....	30
Figure 17: 100/200 Amp Meter Pole, Overhead Feeder .....	31
Figure 18: 320 Amp Meter Pole, Underground Feeder .....	32
Figure 19: 320 Amp Meter Pole, Overhead Feeder .....	33
Figure 20: Wiring of Two Meters, Overhead Service .....	36
Figure 21: Three to Six Meters, Overhead Service .....	37
Figure 22: Underground Service Detail.....	39
Figure 23: Underground Service Detail (Continued) .....	40
Figure 24: Underground Service Structure .....	41
Figure 25: Small Underground Service Structure.....	42
Figure 26: 200/320 Amp Underground Service .....	45
Figure 27: 200 Amp Meter Socket, Underground Service.....	46
Figure 28: 200 Amp Meter Socket, Network (120/208), Underground Service .....	47
Figure 29: 200 Amp Combination Meter Socket, Underground Service.....	48
Figure 30: 200 Amp Combination Meter Socket, Network (120/208), Underground Service .....	49
Figure 31: 320 Amp Meter Socket, Underground Service.....	50
Figure 31A: 320 Amp Meter Socket, Network (120/208), Underground Service .....	51
Figure 32: 320 Amp Combination Meter Socket, Underground Service.....	52
Figure 32A: 320 Amp Combination Meter Socket, Network (120/208), Underground Service .....	53
Figure 33: Meter Pedestal.....	54
Figure 34: 600 Amp to 800 Amp, Current Transformer Metering, Underground Service .....	58
Figure 35: Wiring of two Meters, Underground Service .....	61
Figure 36: Three to Six Meters, Underground Service .....	62
Figure 37: Seven or More Meters, Underground Service.....	64

## 1.0 INTRODUCTION

Liberty constantly strives to maintain a high standard of service to all Customers. This booklet has been prepared for use by Customers, architects, engineers, electrical contractors, and local inspecting authorities so that they may receive full benefit from our service. We believe you will find it helpful when planning new electrical installations, upgrading, or adding additional equipment. Copies are available at the Liberty Central Region Corporate office, service centers, and online through the website:

<https://central.libertyutilities.com/all/residential/new-service/service-standards.html>

All holders of Requirements for Electric Service and Meter Installations booklets are encouraged to submit comments to aid in future revisions. Please submit comments as follows:

1. Give the section, paragraph, and page number to which the comment pertains.
2. Submit comments in writing, giving details, sketches, drawings, and all supporting pertinent information.
3. Mail or Email to:

LIBERTY  
Standards Engineering  
PO Box 127  
Joplin MO 64802  
Email: Jeff.Brown@libertyutilities.com

The impression generally prevails that compliance with the National Electrical Code (NEC), or the various electrical ordinances guarantees to the Customer a wiring installation complete and adequate for the full use of electric service now and in the future. This is not necessarily the case. The NEC and these guidelines are designed to provide the minimum requirements considered necessary for safety. **(The NEC, Article 90.2(B) itself states, "...Compliance therewith and proper maintenance will result in an installation that is essentially free from hazard, but not necessarily efficient, convenient, or adequate for good service or future expansion of electrical use.")** Careful design and installation often results in a wiring system that exceeds NEC requirements.

LIBERTY, as a utility, must meet the requirements of the National Electrical Safety Code (NESC), which sometimes differ from the National Electrical Code (NEC).

**The Company shall have the right to disconnect or refuse service to any installation which violates local, municipal, NEC or NESC regulations. The Company shall also have the right to disconnect or refuse service for installations that are hazardous to the public, or negatively impacts service to other Customers, or Company facilities.**

Except for the installation and maintenance of its own property, Liberty does not install or repair wiring or equipment beyond the point of delivery. Therefore, Liberty is not responsible for the voltage levels beyond the point of delivery and does not assume any responsibility for Customer facilities beyond the point of delivery. Your cooperation will be greatly appreciated and will enable you to receive prompt and satisfactory service.

## 2.0 GENERAL INFORMATION

### 2.1 DEFINITIONS

<b>Company</b>	LIBERTY
<b>Conduit</b>	Pipe used to protect the electrical conductors. Rigid Steel or Schedule 80 Electrical Grade PVC is required on the wall when an underground service is provided.
<b>Conduit Strap</b>	A properly sized strap or clamp used with screws or nails to securely attach conduit to the structure.
<b>Conduit Reducer</b>	A fitting that provides a way to connect together different sized conduits.
<b>Conduit Vent</b>	A fitting used to provide an outlet so that gases or fluids can be released externally from the conduit. This is commonly used in hilly terrain.
<b>Contribution-in-Aid Construction</b>	An amount to be paid to the Company by a Customer or developer when of the Company has to install electrical facilities over and above what is normally required to provide service. This is required when the cost to serve is not justified by the expected revenue provided by the service.
<b>Customer</b>	User of the Company's electric service or user's authorized representative (architect, engineer, electrical contractor, etc.).
<b>Drip Loop</b>	Short length of the customer's service entrance conductors (wire) extending out of the weatherhead which allows connection to the Company's service drop.
<b>Emergency Disconnect</b>	<b>A properly labeled means of disconnect, with sufficient short-circuit current rating, located in a readily accessible outdoor location that can be used by first responders or utility personnel to remove power from a structure. Refer to NEC 230.85 for details and requirements.</b>
<b>Inspector or Inspection Authority</b>	A person or agency authorized by a governmental body to inspect and approve electrical installations.
<b>Interconnection-Cogeneration and Small Power Producers</b>	An electric service where co-generators and small power producers operate in parallel with the Company's electric system. Energy may flow in either direction through an interconnection.
<b>Intersystem Ground Connector (Intersystem Bonding Termination)</b>	A device that provides a means for connecting communication system(s) grounding conductor(s) and bonding conductor(s) at the service equipment or at the disconnecting means for buildings or structures supplied by a feeder or branch circuit.
<b>Line of Sight</b>	Is a straight line from the Liberty designated service source, i.e., Service Pole, Transformer Pole, Pad Mounted Transformer, Secondary Pedestal, etc. to the Liberty Point of Delivery. (See Figure 3)
<b>Main Disconnect</b>	This term as used in this document refers to a combination of a disconnecting and overcurrent protection device, e.g., fuse and manual switch or circuit breaker. Liberty recommends that a circuit breaker be used to accomplish this function.
<b>Manufactured Home/Building</b>	Shall be defined by the following requirements: <ul style="list-style-type: none"><li>A. The structure shall be installed on and secured to a permanent foundation. This does not mean block piers with cable or strap tie downs.</li><li>B. The structural integrity of the manufactured home is sufficient to support the metered service equipment per NEC 550.32.</li></ul>
<b>Meter Loop</b>	Customer provided wire and enclosure connecting the Customer's service equipment to the Company's service drop. Consists of the following: Point of Attachment, wires, weatherhead, conduit, conduit straps, and meter socket/disconnect combination. These can be separate components.
<b>Mobile Home</b>	Shall be defined as any other type of structure moved to a site that does not match the Manufactured Building definition of this document.




<b>NEC</b>	The latest edition of the NFPA 70 National Electrical Code.
<b>NESC</b>	The latest edition of the IEEE National Electrical Safety Code
<b>Point of Attachment</b>	The point <b><i>designated by the Company</i></b> at which the Company's service drop is attached to the Customer's facility. Can be attached to the structure or to rigid steel conduit. It must be capable of withstanding a 200 pound continuous pull in the direction of the service drop and be electrically insulated from the structure.
<b>Point of Delivery</b>	The point <b><i>designated by the Company</i></b> where the Company's facilities terminate at the Customer's facilities.
<b>Readily Accessible</b>	Capable of being reached quickly, for operation, renewal, or inspections without requiring those to whom ready access is a requisite to climb over or remove obstacles or resort to portable ladders, etc.
<b>Self-Contained Meter Socket</b>	A meter socket that is installed in line with the service entrance or lateral conductors. If the socket were replaced with conductor, the power could flow straight through to the service equipment.
<b>Service</b>	The supply by the Company of electricity to the Customer, including the readiness and availability of electrical energy at the point of delivery, at the standard available voltage whether or not utilized by the Customer.
<b>Service Drop</b>	The overhead service conductors between Company's last pole or other aerial support to and including the connectors to the service entrance conductors at the point of delivery to the Customer's property.
<b>Service Entrance</b>	Customer owned conductors and enclosures connecting the Customer's service equipment to the Company's service drop or service lateral.
<b>Slip Joint</b>	A fitting that provides a slip fit adjustment of PVC conduit extending from an electric service box on a building to an underground electric service line. The fitting allows for subsidence of the ground level without creating excessive force on the service box.
<b>Service Lateral</b>	The underground service conductors between the Company's secondary pedestal or transformer, including any risers at a pole or other structure and the point of delivery.
<b>Sweep Elbow or ELL</b>	Conduit Bend.
<b>Undisturbed Earth</b>	Soil that has not been moved by construction or re-compacted soil that approximates such. In engineering terms, it is top soil or clay void of rotting debris that has been re-compacted in 1 foot lifts to the desired level using a vibrating roller or sheep's-foot roller and achieving a 95% modified Proctor Density at each lift.
<b>Wire Size</b>	This refers to the AWG (American Wire Gauge) designation of copper wire unless otherwise specified. Should another approved conductor material be used, a size having the equivalent current carrying capacity shall be selected.

## DEFINITIONS ONLY

### REFER TO INSTALLATION SPECIFICATION AND FIGURES FOR CONSTRUCTION DETAILS.

**Meter Loop - Customer provided** wire and enclosure connecting the customer's service equipment to the Company's service drop. Consists of the following: **Point of Attachment, wires, weatherhead, conduit, conduit straps, and meter socket.**

**Point of Attachment -** The point as *designated by the Company* at which the Company's service drop is attached to the Customer's facility. Can be attached to the structure or to rigid steel conduit. It must be capable of withstanding a 200 pound continuous pull in the direction of the service drop and be electrically insulated from the structure.



**Weatherhead -** Device attached to the top of the conduit to protect the enclosed conductors from the weather.

**Conduit Strap -** properly sized strap used with screws or nails to securely attach conduit to the structure.

**Conduit -** Pipe used to protect the electrical conductors.

**Self-Contained Meter Socket -** Often called the "Meter Base". **Customer provided** enclosure that holds the Company's metering device.

**Intersystem Ground Connector -** A connector block designed to provide a grounding path so that others, i.e. cable TV, telephone, may have easy access to ground bonding. This is as per NEC 250.94 (A).

**Ground Wire -** Referred to as "Grounding Electrode Conductor" by the NEC. Conductor used to connect the Ground Rod to the meter socket grounding connector at the service entrance. It must be securely attached to the structure.

**Drip Loop -** Short length of the customer's service entrance conductors (wire) extending out of the weatherhead which allows connection to the Company's service drop.

**Meter -** Company provided device to measure energy consumption.

**Main Disconnect - Customer provided** device by which conductors of a service circuit can be disconnected from their source of energy. The disconnect shall be located on the exterior of the structure either as a combination socket or a separate disconnect. If more than one disconnect is required, they shall all be placed at this location.

**Ground Rod Clamp -** Clamp specifically designed to connect ground wire to ground rod.

**Ground Rod -** Referred to as a "Grounding Electrode" by the NEC. Copper clad steel rod, 5/8" x 8', driven in undisturbed earth as close to the service entrance as possible.

02/05/21	DER
03/13/18	KMH
12/30/04	SDS
REVISIONS	




#### DEFINITIONS

DRAWN: JEB	DWG. NO. G18A2020
SCALE: NTS	FIGURE 1
DATE: 5/13/96	


**Figure 1: Definitions**

## DEFINITIONS ONLY

**REFER TO INSTALLATION SPECIFICATION AND FIGURES  
FOR CONSTRUCTION DETAILS.**




**Undisturbed Earth** - Soil that has not been moved by construction or recompact soil that approximates such. In engineering terms, it is top soil or clay void of rotting debris that has been recompact in 1 foot lifts to the desired level using a vibrating roller or sheeps-foot roller and achieving a 95% modified Proctor Density at each lift.

02/04/21	DER	 Liberty	DEFINITIONS	
07/17/19	KMH		DRAWN: SDS	DWG. NO. G18A2021
SDS	01/26/09		SCALE: NTS	FIGURE 2
	REVISIONS		DATE: 11/06/06	

**Figure 2: Definitions**

# DEFINITIONS ONLY

LINE OF SIGHT CAN BE DETERMINED BY AN ANGLE OF 160 DEGREES FROM THE METER SOCKET LOCATION.



02/05/21 DER	Liberty	DEFINITIONS	
04/19/18 KMH		DRAWN: SDS	DWG. NO. G18A2022
REVISIONS		SCALE: NTS	FIGURE 3
		DATE: 10/01/09	

Figure 3: Definitions

## 2.2 AVAILABILITY AND LOCATION OF SERVICE

Before construction is started, the Customer shall request the Company to designate a point of delivery and submit appropriate load data to the Company. The load data should include the anticipated demand and list of equipment. The Customer shall provide a set of building plans, a survey, and a copy of the warranty deed. It is requested that the Customer provide the building plans as an AutoCAD file (.DWG) format.

It is important that the Company and Customer be in agreement on the planned location of all service-related equipment before construction is started. This equipment includes, but may not be limited to; meter sockets, risers, pedestals, conduit and trench location, pull boxes, padmounted transformers, CT/connection cabinets, pole, lines and anchors.

The Customer is responsible for contacting customer service in order to submit a request to open a billing account before any permanent service can be installed. Customer Service can be reached by calling:

(800) 206 – 2300.

Failure to comply could result in time delays and/or additional cost to the Customer.

## 2.3 TYPE AND CHARACTER OF SERVICE

1. It is essential that the customer consult the Company regarding type of service which can be furnished at a particular location before proceeding with purchase of equipment or installation of wiring.
2. The voltage and/or number of phases which will be supplied will depend on the type, size and location of the load, and existing Company facilities.
  - a. The table below lists the standard service voltages that are available.

	Pole Mounted Transformer	Pad Mounted Transformer
SINGLE PHASE	120/240 Volts, 3-Wire Up to 167 KVA	120/240 Volts, 3-Wire Up to 167 KVA
SOME COMMERCIAL AREAS*	120/208, 3-Wire	120/208, 3-Wire

- b. Single-phase, three-wire service will be provided according to the following:
  - (1) Customers located in predominantly residential areas will normally be provided with only single-phase 120/240 volt service.
  - \*(2) Customers located in commercial/industrial areas may be provided with 120/208 volt service. \*Contact the Company for more details.

## 2.4 GENERAL REQUIREMENTS

1. The Customer's wiring and electrical equipment shall be safe, in conformance with the NEC and with all applicable federal, state, and local codes and ordinances.
2. The Main Disconnect ampacity determines the wire size used in the Service Riser as well as the wire size from the Meter Socket to the Main Disconnect.
3. **All wiring installations must be inspected and approved by an authorized electrical inspector as required by governmental authority.**

**The Company shall have the right to disconnect or refuse service to any installation which violates local, municipal, NEC or NESC regulations. The Company shall also have the right to disconnect or refuse service for installations that are hazardous to the public or negatively impact service to other Customers or Company facilities.**

4. Before service can be connected, the 911 address must be displayed at the location.

## 2.5 ALTERATIONS AND ADDITIONS

1. **SERVICE CONNECTIONS, METERS, OR METERING EQUIPMENT SHALL NOT BE REMOVED OR RELOCATED EXCEPT BY EMPLOYEES OF THE COMPANY OR ITS AUTHORIZED AGENTS.**
2. Connection to the Customer's premises is made with facilities designed to properly supply adequate electric service for the Customer's operation using information provided at the time of application for service. Therefore, no additions of major load, or alterations of the Customer's installation should be made without first notifying the Company. Failure to provide such notification may affect the quality and reliability of the Customer's own service, as well as that of other Customers.
3. When alterations or repairs require the relocation or temporary removal of service drop wires, meters and metering equipment, the Customer shall make appropriate advance arrangements with the Company to perform the relocation or temporary removal. The new location must be approved by the Company before the Customer begins work. All alterations or repairs must meet the applicable codes that are in effect at the time work is done. When alterations or repairs have been satisfactorily completed by the Customer and the necessary inspection approvals obtained, the Company will make the connections to provide service.

**4. Since *serious injury or death* could result from a person coming in contact with an energized electrical circuit or equipment, neither the Customer nor the Customer's agents shall remove an energized meter from its socket. Meters are not designed to be a disconnecting device under load. Arcing, fire, explosion, etc. could occur with the possibility of burns, injury, or death as well as damage to adjacent or surrounding structures and equipment. The Customer will be held legally responsible for such injury, death, or damage if caused by the unauthorized breaking of the seals, tampering, or otherwise interfering with the Company's meter or other equipment of the Company installed on the Customer's premises. No one, except authorized employees or agents of the Company, will be allowed to make any repairs or adjustments to any meter or other equipment belonging to the Company. The Company will be responsible for disconnecting service and removing the meter prior to the repair or replacement of the Customer's meter socket.**

## **3.0 METERING**

### **3.1 GROUNDING**

#### **1. GENERAL**

Unless otherwise noted, the Customer shall supply and install a 5/8" x 8' ground rod with ground rod clamp outside of the building wall. It shall be installed in accordance with NEC 250.53 and be within two (2) feet of the structure at the meter socket location. If other grounding methods are used, all grounding systems must be bonded together as per NEC.

#### **2. SELF – CONTAINED**

When using self-contained meter sockets, the ground wire shall originate at the factory installed grounding connector in the meter socket and terminate at the ground rod clamp on the ground rod. The size of the ground wire shall be as specified in the applicable drawings.

#### **3. CURRENT TRANSFORMER (CT)**

When the metering installation requires the use of current transformers, a single ground rod may not be adequate. Consult the NEC for further information.

#### **4. MINIMUM GROUND WIRE**

For services 320 amps or less, refer to the tables in the applicable drawings. For services larger than 320 amps, consult the NEC.

### **3.2 METERING EQUIPMENT LOCATIONS**

1. The metering equipment shall be located outdoors and approved by the Company.
2. Metering equipment shall be located where it is readily accessible to Company employees without special keys or entry requirements (public entry).
3. Metering accuracy is of utmost importance to the Company and its Customers. Therefore, any location where the environment could affect the accuracy of the meter will not be acceptable. These conditions could include, but are not limited to corrosion, vibration, dust, magnetic interference, etc.

## 4.0 INFORMATION APPLYING TO ALL SERVICES

1. There will only be one service voltage available at a location, and only one point of delivery for each building, except as allowed by the NEC and approved by the Company. If multiple service points are approved by the Company, the service points shall be marked as per NEC 230.2.E. Engraved plaques shall be attached with screws, bolts, or rivets.
2. An emergency disconnect shall be provided and labeled as required by and in accordance with NEC 230.85
3. **The point of delivery shall be designated by the Company prior to beginning construction.**
4. **All utilities must be notified, and all underground facilities located and marked prior to any excavation. This shall include any Customer owned facilities.**
5. All service entrance facilities, including meter sockets, shall be located in an exposed and readily accessible area.
6. **Copper conductors are highly recommended.** Where allowed by local authority, aluminum conductors may be installed per NEC requirement; provided the meter socket is approved for use with aluminum conductors, and a corrosion inhibiting compound recommended by the cable manufacturer is properly applied to the meter socket terminals. **Conductor ampacities used in the wire tables are based on 75 degrees C as per NEC 310.16 as modified by NEC 310.15.**
7. When an existing service entrance using copper conductors is replaced by a service entrance using aluminum conductors, the existing meter socket, if not marked AL-CU, must be replaced with one approved for use with aluminum conductors.
8. Service entrance conductors between the Company's point of delivery and the self – contained metering point, or the first disconnect shall be enclosed in conduit. **Troughs and electrical gutters are not allowed on the Company's side of disconnects on the outside of the building.**
9. Unless otherwise noted, the conduit is to be galvanized rigid steel. **Water pipes, sewer pipes and / or fittings are NOT acceptable.** Unless otherwise stated, all sweep ells shall be rigid steel. The minimum sweep radius according to diameter will be as follows; 4" – 16", 3" – 13", and 2" – 9.5".
10. The neutral conductors of all services shall be grounded at the metering point as shown in the applicable drawings.
11. All neutral conductors shall be clearly marked with white tape at the point of delivery and at the meter location.
12. **Bypass levers are allowed on 320 Amp meter sockets only. Plunger style bypass mechanisms are not allowed.**




## 5.0 TEMPORARY SERVICES

1. The Company must be provided with detailed plans of each installation where temporary service is to be supplied. Installations requiring special service, meter, or other work for construction purposes, exhibits of short duration, etc., **will be made at the expense of the Customer.**
2. Temporary services over 300 feet are not available. **The Company will not be responsible for damage done to equipment with temporary services.**
3. **Temporary service equipment shall not be installed on trees or the Company's Poles.**
4. Temporary installation of service entrance, other wiring, and meters shall meet the same requirements as permanent installations, including inspection and approval.
5. **Temporary single phase service for construction purposes may be provided from either overhead or underground facilities. Arrangements for temporary construction service are shown in Figures 4, 5, and 6.**
6. Prior to connection of permanent service, all temporary service drops, or temporary construction wires or cables shall be removed from the finished structure's permanent distribution panels.
7. The typical temporary service is 120/240v, single phase. Single phase temporary service requiring over 100 amps capacity may be available. Contact the Company for more details; additional costs may apply.

**8. All temporary installations shall be safe and in good working condition as judged by a Company field representative before the service will be connected.**

9. Temporary service will be available at the site as long as construction is in progress or is otherwise limited by the Local Authority. Once the project is substantially completed, the temporary service shall be disconnected.
10. Liberty is not required to provide electric service to temporary Customers at locations that require the extension of Company lines unless the full cost of erection and removal, including indirect costs of construction, of the extension is contributed by the Customer.



Service Drop Minimum Clearances	
12'	Above Sidewalks
16'	Above Residential Driveways
18.5'	Above Public Driveways, Alleys, Roads, and Other Areas Subject to Truck & Construction Traffic.

Refer to NEC for Ground Fault Circuit Interrupter Requirements.

**CAUTION!**  
Contact All Utilities Before Digging or Staking.

**All Equipment Furnished and Installed By Customer Unless Otherwise Noted.**

Service Size	Minimum	
	Neutral*	Line
100 Amp	#4 Cu.	#4 Cu.
	#2 AL.	#2 AL.

\* Neutral May Be Reduced Under Specific Conditions Allowed By NEC.

Service Size	Ground Wire
100 Amp	#6 Cu.

02/04/21	DER
07/15/19	KMH
01/18/13	SDS
10/01/09	SDS
07/15/06	SDS
05/17/05	SDS
01/01/97	AMA
REVISIONS	

Temporary Service From Overhead Facilities



DRAWN: LU	DWG. NO. G18A2023
SCALE: NTS	FIGURE 4
DATE: 01/01/95	

Figure 4: Temporary Service from Overhead Facilities

Refer to NEC for Ground Fault Circuit Interrupter Requirements.


Service Size	Minimum	
	Neutral*	Line
100 Amp	#4 Cu.	#4 Cu.
	#2 AL.	#2 AL.

\* Neutral May Be Reduced Under Specific Conditions Allowed By NEC.




Temporary Meter Loop Shall Be As Shown.

**CAUTION!**  
Contact All Utilities Before Digging or Staking.



Service Drop Minimum Clearances	
12'	Above Sidewalks
16'	Above Residential Driveways
18.5'	Above Public Driveways, Alleys, Roads, and Other Areas Subject to Truck & Construction Traffic.



All Equipment Furnished and Installed By Customer Unless Otherwise Noted.

02/05/21	DER
07/15/19	KMH
02/18/13	SDS
07/15/06	SDS
05/17/06	SDS
REVISIONS	





Temporary Service From Underground Facilities	
DRAWN: LU	DWG. NO. G18A2024
SCALE: NTS	FIGURE 5
DATE: 01/01/97	

Figure 5: Temporary Service from Underground Facilities

Refer to NEC for Ground Fault Circuit Interrupter Requirements.

Service Size	Minimum	
	Neutral*	Line
100 Amp	#4 Cu.	#4 Cu.
	#2 AL.	#2 AL.



\* Neutral May Be Reduced Under Specific Conditions Allowed By NEC.



The Company will make this connection. Provide a minimum of 3' of wire.

Temporary Meter Loop Shall Be As Shown.

**CAUTION!**  
Contact All Utilities Before Digging or Staking.



The Company will make this connection. Provide a minimum of 3' of wire.

All Equipment Furnished and Installed By Customer Unless Otherwise Noted.

02/05/21	DER
07/15/19	KIMH
02/18/13	SDS
07/15/06	SDS
REVISIONS	



Temporary Service From Underground Facilities (Continued)	
DRAWN: LU	DWG. NO. G-18A2025
SCALE: NTS	FIGURE 6
DATE: 01/01/97	

Figure 6: Temporary Service from Underground Facilities (Continued)


**RESERVED FOR FUTURE USE**

**Figure 7: (Future Use)**

## 6.0 OVERHEAD SERVICES

### 6.1 GENERAL INFORMATION

1. The Customer shall provide an insulated Point of Attachment within 24" of the weatherhead which is capable of withstanding a continuous force of 200 lbs. in the direction of pull of the Service Drop. The weatherhead shall be above the point of attachment, where practical.
2. A minimum of 24 inches of service entrance conductor shall be provided by the Customer extended from a single weatherhead for connection to the service drop.
3. The Customer shall provide a clear and unobstructed path for the Company's service drop to the attachment point. The Customer shall request the Company to designate the location of the point of delivery for each service location before construction is started. This shall be done to increase the reliability of electric service. Trees growing into or near power lines are one of the most common causes of power outages. Help avoid the need for future trimming by planting the right tree in the right place. For a list of appropriate trees for the TALL ZONE, MEDIUM ZONE AND LOW ZONE pictured below, please contact your Liberty representative.



4. The point of attachment of the service drop conductors shall be located by the Customer so as to allow not less than the minimum clearances for the service drop as shown in the table below. Greater clearances may be required by local authorities. **In no case shall the attachment height be lower than 12' above final grade.**

<b>MINIMUM CLEARANCES OF SERVICE DROP CABLES<sup>(1)(2)</sup></b>	
Above roads, streets, alleys, parking lots, commercial and industrial driveways subject to truck traffic .....	18.5 feet
Above residential driveways.....	16 feet
Roofs, decks, and loading ramps accessible to vehicles but not subject to truck traffic..	16 feet
Above spaces and ways subject to pedestrians or restricted traffic only .....	12 feet
Over or under roofs, decks, porches, or balconies readily accessible to persons <sup>(3)</sup> .....	10 feet
Over roofs or projections not readily accessible to persons <sup>(4)</sup> .....	8.5 feet
Horizontal to any walls, projections, porches, balconies, ladders, stairs, fire escapes, or other similarly attached structures.....	5 feet
Horizontal from directly below conductor to edge of swimming pool or fixed pool related structure (Applies to above or in ground swimming pools) .....	10 feet
From service conductors not enclosed in conduit to windows designed to be opened or doors <sup>(5)</sup> .....	3 feet

*(1) Values in this table only apply to cables between 0-750V meeting definitions of NESC Rule 230C2 or 230C3 at final sag conditions. Consult the Company for all situations not covered in this table.*

*(2) The point of attachment shall normally be 2' - 3' higher than these minimum required clearances to allow for sag of the service cable.*

*(3) Roofs with solar panel installations shall be considered accessible to persons for the purposes of this publication*

*(4) Consult the Company before following any exceptions listed in NEC Rule 230.24*

*(5) Applies to conductors at attachment point. Conductors meeting the definition of NESC Rule 230C3 run above the top level of a window shall be permitted to be less than the 3 feet requirement. Does not apply to windows **not** designed to be opened.*

5. Street access driveways, where vehicular traffic may pass under service conductors, must maintain the minimum clearances from ground to service conductors required for roads, streets, alleys, and parking lots in the above table. For further details and items not covered above, contact the Company.

**6. The point of delivery will be at the weatherhead connections.**

## 6.2 100 AMP, 200 AMP, AND 320 AMP SINGLE PHASE OVERHEAD SERVICES

### A. General Notes:

1. Service entrance conductors, 5/8" x 8' copper clad steel ground rod, ground rod clamp, ground wire, conduit, conduit straps, weatherhead, lock nuts, bushings, meter socket, meter socket hub, service drop attachment device, and miscellaneous mounting hardware furnished and installed by the Customer.
2. Meter, service connectors, and service drop furnished and installed by Company.
3. The meter socket should be "readily accessible" (see definitions). The Company requires a level and unobstructed workspace of 78 inches tall, 18 inches on either side, and 48 inches in front of the meter socket. Prior approval is required for placement of the meter socket in alleyways or areas where it may be subjected to damage.
4. The 100 Amp, 200 Amp and 320 Amp meter sockets shall meet the following specifications:
  - a. The latest revision of U.L. 414 and ANSI C12.7 Standards.
  - b. NEMA 3R compliant enclosure
  - c. Must be U.L. listed.
  - d. Must have grounding connector for triplex.
  - e. Lug size – 2/0 minimum.
  - f. On 120/208v services, the customer must provide the meter socket with 5<sup>th</sup> lug installed in the 9 o'clock position.
  - h. This is not a complete list of criteria for acceptance. See Appendix A for list of approved meter sockets.**
5. Installation requiring a steel service mast shall be installed by the Customer as specified in Figure 9.

### B. Mounting:

1. Meter socket, ground wire, and conduit shall be surface mounted and securely fastened to the structure. The meter socket shall be installed in a level and plumb position. ***Flush mounted or recessed metering equipment and service riser conduit embedded in a wall will not be permitted.***
2. Where the exterior wall is other than brick or concrete blocks, a supporting frame shall be installed behind the exterior wall to provide a solid mounting surface for the meter socket.
3. Meter sockets, metering cabinets, and conduit straps shall be installed with the following:
  - a. Lead anchors or double helix concrete screws shall be used with brick or solid concrete surfaces.
  - b. Toggle bolts shall be used with other masonry siding.
  - c. Wood screws shall be used with solid wood surfaces.
  - d. All mounting hardware shall be minimum #12(1/4") corrosion resistant screws.
  - e. A minimum of 4 fasteners shall be used to install any socket or cabinet unless specifically stated otherwise.
4. An intersystem bonding termination bar shall be installed in accordance with NEC 250.94 to facilitate the connection of other utility's ground to a common ground. The location of this device shall be located directly below the meter socket or meter combination socket.
  - a. See Appendix A for list of approved intersystem bonding termination bars.**



C. Connections:

1. Do not score line or load wire when removing insulation.
2. The Customer shall use wire brush or sandpaper to clean all conductors, apply a non-grit type inhibitor and tighten to manufacturer's specifications.

D. Conductor Marking:


All neutral conductors shall be clearly marked with white tape at the point of delivery and at the meter socket.

Minimum Attachment Height shall be 12' above final grade. The Customer shall provide an insulated Point of Attachment within 24" of the Weatherhead which is capable of withstanding a continuous force of 200 lbs. in the direction of pull of the Service Drop.

A minimum of 24" of wire shall be provided by the Customer. The Neutral shall be marked with white tape. The wire shall be marked or listed as Sunlight Resistant as per NEC 310.10 (D).

The path to the Service Pole shall be clear of trees and building debris and materials.

Service Drop Minimum Clearances	
12'	Above Sidewalks
16'	Above Residential Driveways
18.5'	Above Public Driveways, Alleys, Roads, and Other Areas Subject to Truck & Construction Traffic



Service Size	Ground Wire
100 Amp	#6 Cu.
200 Amp	#4 Cu.
320 Amp	1/0 Cu.

All Grounding Systems shall be bonded together.  
5/8" X 8' Copper Clad Steel Ground Rod installed external to Building.

Service Size	Wire Sizes		Conduit Size	Wire Sizes		Conduit Size	Conduit Type***
	Minimum			Recommended			
	Neutral**	Line		Neutral**	Line		
100 Amp*	#4 Cu.	#4 Cu.	1 1/4"	#3 Cu.	#3 Cu.	1 1/4"	Galv. Rigid Steel
	#2 AL.	#2 AL.	1 1/4"	#1 AL.	#1 AL.	1 1/2"	Galv. Rigid Steel
200 Amp	2/0 Cu.	2/0 Cu.	2"	3/0 Cu.	3/0 Cu.	2"	Galv. Rigid Steel
	4/0 AL.	4/0 AL.	2"	250 AL.	250 AL.	2 1/2"	Galv. Rigid Steel
320 Amp	2 - 4/0 Cu.	2 - 4/0 Cu.	3"	2 - 4/0 Cu.	2 - 4/0 Cu.	3"	Galv. Rigid Steel
	2 - 300 AL.	2 - 300 AL.	4"	2 - 300 AL.	2 - 300 AL.	4"	Galv. Rigid Steel

\*100 Amp allowed on overhead service only  
 \*\*Neutral may be reduced under specific conditions allowed by NEC  
 \*\*\* Other types of conduit allowed depending on local code

Ground Rod and Wire **MUST** be Installed and Ground Wire **MUST** be attached to the structure before Service will be Connected.

**Notes:**

1. If minimum vertical clearance cannot be maintained with the installation of an attachment as shown above, the **Customer** shall install a rigid steel service mast as shown in Figure 9.
2. Connections between the Service Drop and Service Entrance Conductors shall be made **by Company Personnel** below the Weatherhead, forming a Drip Loop.
3. Other types of conduit may be allowed depending on Local Code Requirements. These may include EMT, Electrical Grade PVC, and Rigid Aluminum. **However, the Service Drop shall not be attached to any of these.**
4. 100 amp, 200 amp and 320 amp meter sockets shall be furnished **by the customer**. Bypass lever allowed on 320 amp meter socket only.
5. The disconnect shall be located on the exterior of the structure either as a combination socket or an separate disconnect. Emergency disconnects shall be installed according to NEC 230.85. If more than one disconnect is required, they shall all be placed at this location. It shall not be closer than 1' nor farther than 1' from the meter socket.

**All Equipment Furnished and Installed By Customer Unless Otherwise Noted.**



 Liberty	100/200/320 Amp Overhead Service	
	REV: 7	DWG NO: G182027
	SCALE: NTS	FIGURE 8
DATE: 06/06/2024		

Figure 8: 100/200/320 Amp Overhead Service



**All Equipment Furnished and Installed By Customer Unless Otherwise Noted.**




**100/200/320 Amp Steel Service Mast**

REV:	7	DWG NO:	G18A2028
SCALE:	NTS	FIGURE 9	
DATE:	06/07/2024		

**Figure 9: 100/200/320 Amp Steel Service Mast**

Service Size	Wire Sizes			
	Minimum		Recommended	
	Neutral**	Line	Neutral**	Line
100 Amp*	#4 Cu.	#4 Cu.	#3 Cu.	#3 Cu.
	#2 AL.	#2 AL.	#1 AL.	#1 AL.
200 Amp	2/0 Cu.	2/0 Cu.	3/0 Cu.	3/0 Cu.
	4/0 AL.	4/0 AL.	250 AL.	250 AL.

\* 100 Amp allowed on overhead service only.  
 \*\* Neutral May Be Reduced Under Specific Conditions Allowed By NEC.



**All Equipment Furnished and Installed By Customer Unless Otherwise Noted.**

02/05/21	DER
06/15/19	KMH
12/26/08	SDS
05/17/05	SDS
01/01/97	AMA
REVISIONS	



100/200 Amp Meter Socket, Overhead Service	
DRAWN: LU	DWG. NO. G18A2029
SCALE: NTS	FIGURE 10
DATE: 01/01/95	

Figure 10: 100/200 Amp Meter Socket, Overhead Service

**Note:**  
**This application for**  
**120/208v, 3 wire service.**

Service Size	Wire Sizes			
	Minimum		Recommended	
	Neutral**	Line	Neutral**	Line
100 Amp*	#4 Cu.	#4 Cu.	#3 Cu.	#3 Cu.
	#2 AL.	#2 AL.	#1 AL.	#1 AL.
200 Amp	2/0 Cu.	2/0 Cu.	3/0 Cu.	3/0 Cu.
	4/0 AL.	4/0 AL.	250 AL.	250 AL.

\* 100 Amp allowed on overhead service only.  
 \*\* Neutral May Be Reduced Under Specific Conditions Allowed By NEC.

Neutral shall be marked with white tape at Meter Socket and Weatherhead.


This wire must have white insulation and will be connected as shown. This wire will be provided and installed by the Customer on **Approved Meter Sockets**.

The Customer will provide and install the 5th lug on **Approved Meter Sockets**. For a list of these, refer to **Appendix A**.

**DO NOT Install Multiple Conductors Under One Lug.**

Neutral shall be marked with white tape at Meter Socket and Weatherhead.

1" (MIN)  
 1' (MAX)



**DO NOT Install Multiple Conductors Under One Lug.**

No Bypass Lever Allowed.

**Ground Connector**  
 The Ground Wire shall not be carried through this connector to the Main Panel.

Service Size	Ground Wire
100 Amp	#6 Cu.
200 Amp	#4 Cu.

**All Equipment Furnished and Installed By Customer Unless Otherwise Noted.**

02/05/21 DER	07/15/19 KMH	12-26-08 SDS	07-15-06 SDS	05-17-06 SDS	REVISIONS
--------------	--------------	--------------	--------------	--------------	-----------



100/200 Amp Meter Socket, Network (120/208), Overhead Service	
DRAWN: LU	DWG. NO. G18A2030
SCALE: NTS	FIGURE 11
DATE: 07/01/97	

Figure 11: 100/200 Amp Meter Socket, Network (120/208), Overhead Service

Label disconnect as required by NEC

Service Size	Wire Sizes			
	Minimum		Recommended	
	Neutral**	Line	Neutral**	Line
100 Amp*	#4 Cu.	#4 Cu.	#3 Cu.	#3 Cu.
	#2 AL.	#2 AL.	#1 AL.	#1 AL.
200 Amp	2/0 Cu.	2/0 Cu.	3/0 Cu.	3/0 Cu.
	4/0 AL.	4/0 AL.	250 AL.	250 AL.


\*100 Amp allowed on overhead service only  
 \*\*Neutral may be reduced under specific conditions allowed by NEC

**DO NOT Install Multiple Conductors Under One Lug.**

**DO NOT Install Multiple Conductors Under One Lug.**

Energized parts of service equipment shall be enclosed or guarded in accordance with NEC 230.62

Neutral shall be marked with white tape at Meter Socket and Weatherhead.



Service Size	Ground Wire
100 Amp	#6 Cu.
200 Amp	#4 Cu.

**All Equipment Furnished and Installed By Customer Unless Otherwise Noted.**



100/200 Amp Combination Meter Socket

REV:	3	DWG NO:	G18A2031
SCALE:	NTS	FIGURE 12	
DATE:	06/07/2024		

Figure 12: 100/200 Amp Combination Meter Socket




Label disconnect as required by NEC

Service Size	Wire Sizes			
	Minimum		Recommended	
	Neutral**	Line	Neutral**	Line
100 Amp*	#4 Cu.	#4 Cu.	#3 Cu.	#3 Cu.
	#2 AL.	#2 AL.	#1 AL.	#1 AL.
200 Amp	2/0 Cu.	2/0 Cu.	3/0 Cu.	3/0 Cu.
	4/0 AL.	4/0 AL.	250 AL.	250 AL.

\*100 Amp allowed on overhead service only  
 \*\*Neutral may be reduced under specific conditions allowed by NEC

**Note:**  
 This application for  
 120/208v, 3 wire service.



**All Equipment Furnished and Installed By Customer Unless Otherwise Noted.**




100/200 Amp Combination Meter Socket, Network (120/208), Overhead Service

REV:	4	DWG NO:	G18A2032
SCALE:	NTS	FIGURE 13	
DATE:	06/07/2024		

Figure 13: 100/200 Amp Combination Meter Socket, Network (120/208), Overhead Service

Service Size	Wire Sizes			
	Minimum		Recommended	
	Neutral*	Line	Neutral*	Line
320 Amp	2 - 4/0 Cu.	2 - 4/0 Cu.	2 - 4/0 Cu.	2 - 4/0 Cu.
	2 - 300 AL	2 - 300 AL	2 - 300 AL	2 - 300 AL

\* Neutral may be reduced under specific conditions allowed by NEC.



**All Equipment Furnished and Installed By Customer Unless Otherwise Noted.**

02/04/21	DER
01/27/21	LRs
07/01/19	KMH
03-18-10	SDS
04-01-09	SDS
05-17-05	SDS
01-01-97	AWA
REVISIONS	



320 Amp Meter Socket, Overhead Service

DRAWN: KMH	DWG. NO. G18A2033
SCALE: NTS	FIGURE 14
DATE: 01/27/21	


Figure 14: 320 Amp Meter Socket, Overhead Service



Service Size	Wire Sizes			
	Minimum		Recommended	
	Neutral*	Line	Neutral*	Line
320 Amp	2 - 4/0 Cu.	2 - 4/0 Cu.	2 - 4/0 Cu.	2 - 4/0 Cu.
	2 - 300 AL	2 - 300 AL	2 - 300 AL	2 - 300 AL

\* Neutral may be reduced under specific conditions allowed by NEC.

**Note:**  
**This application for 120/208v, 3-wire service.**



**All Equipment Furnished and Installed By Customer Unless Otherwise Noted.**

02/04/21 DER  
 01/27/21 LRS  
 06/11/20 SMS  
 REVISIONS



320 Amp Meter Socket, Network (120/208), Overhead Service

DRAWN: KMH DWG. NO. G18A2033A  
 SCALE: NTS  
 DATE: 01/27/21

FIGURE 14A

**Figure 14A: 320 Amp Meter Socket, Network (120/208), Overhead Service**


Label disconnect as required by NEC

Service Size	Wire Sizes			
	Minimum		Recommended	
	Neutral*	Line	Neutral*	Line
320 Amp	2 - 4/0 Cu.	2 - 4/0 Cu.	2 - 4/0 Cu.	2 - 4/0 Cu.
	2 - 300 AL.	2 - 300 AL.	2 - 300 AL.	2 - 300 AL.

\*Neutral may be reduced under specific conditions allowed by NEC

**DO NOT Install Multiple Conductors Under One Lug Without Approval From The Company**

**DO NOT Install Multiple Conductors Under One Lug Without Approval From The Company**



**All Equipment Furnished and Installed By Customer Unless Otherwise Noted.**



**320 Amp Combination Meter Socket, Overhead Service**

REV:	3	DWG NO:	G18A2034
SCALE:	NTS	FIGURE 15	
DATE:	06/10/2024		


**Figure 15: 320 Amp Combination Meter Socket, Overhead Service**

Service Size	Wire Sizes			
	Minimum		Recommended	
	Neutral*	Line	Neutral*	Line
320 Amp	2 - 4/0 Cu.	2 - 4/0 Cu.	2 - 4/0 Cu.	2 - 4/0 Cu.
	2 - 300 AL.	2 - 300 AL.	2 - 300 AL.	2 - 300 AL.

\*Neutral may be reduced under specific conditions allowed by NEC

Label disconnect as required by NEC

**Note:**  
This application for 120/208v,  
3 wire service.



**All Equipment Furnished and Installed By Customer Unless Otherwise Noted.**



320 Amp Combination Meter Socket, Network, (120/208), Overhead Service

REV:	3	DWG NO:	G18A2034A
SCALE:	NTS	FIGURE 15A	
DATE:	06/10/2024		

Figure 15A: 320 Amp Combination Meter Socket, Network (120/208), Overhead Service

Security Light May Be Leased From the Company. Customer will not be allowed to install their light on this pole.

The path to the Service Pole shall be clear of trees and building debris and materials.

Pole installed and owned by the Company.

Company Conductors

This Weatherhead shall be located no more than 3' below the top of the Pole.

Two Hole Conduit Strap

A minimum of 24" of wire shall be provided by the Customer. The Neutral shall be marked with white tape. The wire shall be marked or listed as Sunlight Resistant as per NEC 310.10 (D).

Meter Loop (Weatherhead, Service Entrance Wire, Conduit, Meter Socket/Breaker Combination, Ground Wire, Ground Rod Clamp, 5/8" x 8' Ground Rod, Etc.) may be purchased from and installed by the Company on Company pole ONLY.

Attachment furnished and installed by the Company.

Drip-Loop 10' Clearance (Min.) above Finished Grade.

Service Drop Minimum Clearances	
12'	Above Sidewalks
16'	Above Residential Driveways
18.5'	Above Public Driveways, Alleys, Roads, and Other Areas Subject to Truck & Construction Traffic

**Meter Loop Will be Owned and Maintained by the Customer.**

The Meter Pole shall be located within line of sight and within 50' of the Mobile Home/Building it serves; Otherwise see NEC Article 550.32.

This may be a Meter Socket and separate Breaker Enclosure connected by Rigid Conduit.

No Bypass Lever Allowed.

Note: Meter Loop will not be installed on Primary Power Poles.

4' To 6' Above Final Grade Level

Service Size	Ground Wire
100 Amp	#6 Cu.
200 Amp	#4 Cu.

Customer supplied and installed Underground Service Feeder.

Ground Wire



30" Recommended Ditch Depth.

5/8" X 8' Copper Clad Steel Ground Rod and Clamp

Ground Wire and Pole Down Ground are bonded together at the Ground Rod.

Service Size	Wire Sizes		Conduit Size	Wire Sizes		Conduit Size	Conduit Type***
	Minimum			Recommended			
	Neutral**	Line		Neutral**	Line		
100 Amp*	#4 Cu.	#4 Cu.	1 1/4"	#3 Cu.	#3 Cu.	1 1/4"	Galv. Rigid Steel
	#2 AL.	#2 AL.	1 1/4"	#1 AL.	#1 AL.	1 1/2"	Galv. Rigid Steel
200 Amp	2/0 Cu.	2/0 Cu.	2"	3/0 Cu.	3/0 Cu.	2"	Galv. Rigid Steel
	4/0 AL.	4/0 AL.	2"	250 AL.	250 AL.	2 1/2"	Galv. Rigid Steel

\*100 Amp allowed on overhead service only  
 \*\*Neutral may be reduced under specific conditions allowed by NEC  
 \*\*\* Other types of conduit allowed depending on local code

**All Equipment Furnished and Installed By Customer Unless Otherwise Noted.**



100/200 Amp Meter Pole, Underground Feeder

REV:	8	DWG NO:	G18A2035
SCALE:	NTS	FIGURE 16	
DATE:	06/10/2024		

Figure 16: 100/200 Amp Meter Pole, Underground Feeder

Security Light May Be Leased From The Company. Customer will not be allowed to install their light on this pole.

Pole installed and owned by the Company.

Weatherhead shall be located no more than 3' below the top of the Pole.

Attachment furnished and installed by the Company.

Recommended Height as per Table to right and below.

Customer Connectors

Company Conductors

The path to the Service Pole shall be clear of trees and building debris and materials.

Attachment furnished and installed by the Company.

A minimum of 24" of wire shall be provided by the Customer. The Neutral shall be marked with white tape. The bare messenger shall be designated the EGC. The wire shall be marked or listed as Sunlight Resistant as per NEC 310.10 (D).

A minimum of 24" of wire shall be provided by the Customer. The Neutral shall be marked with white tape. The wire shall be marked or listed as Sunlight Resistant as per NEC 310.10 (D).

Drip-Loop 10' Clearance (Min.) above Finished Grade.

Drip-Loop 10' Clearance (Min.) above Finished Grade.

**Meter Loop Will be Owned and Maintained by the Customer.**

Service Drop Minimum Clearances	
12'	Above Sidewalks
16'	Above Residential Driveways
18.5'	Above Public Driveways, Alleys, Roads, and Other Areas Subject to Truck & Construction Traffic.

This may be a Meter Socket and separate Breaker Enclosure connected by Rigid Conduit.

No Bypass Lever Allowed.

Note: Meter Loop will not be installed on Primary Power Poles.

Service Size	Ground Wire
100 Amp	#6 Cu.
200 Amp	#4 Cu.

4' To 6' Above Final Grade Level

Ground Wire

5/8" X 8' Copper Clad Steel Ground Rod and Clamp

Ground Wire and Pole Down Ground are bonded together at the Ground Rod.

Service Size	Wire Sizes		Conduit Size	Wire Sizes		Conduit Size	Conduit Type ***
	Minimum			Recommended			
	Neutral**	Line		Neutral**	Line		
100 Amp*	#4 Cu.	#4 Cu.	1 1/4"	#3 Cu.	#3 Cu.	1 1/4"	Galv. Rigid Steel
	#2 AL.	#2 AL.	1 1/4"	#1 AL.	#1 AL.	1 1/2"	Galv. Rigid Steel
200 Amp	2/0 Cu.	2/0 Cu.	2"	3/0 Cu.	3/0 Cu.	2"	Galv. Rigid Steel
	4/0 AL.	4/0 AL.	2"	250 AL.	250 AL.	2 1/2"	Galv. Rigid Steel

\* 100 Amp allowed on overhead service only.  
 \*\* Neutral May Be Reduced Under Specific Conditions Allowed By NEC.  
 \*\*\* Other types of conduit allowed depending on local code.

**All Equipment Furnished and Installed By Customer Unless Otherwise Noted.**



**100/200 Amp Meter Pole Overhead Feeder**

REV:	6	DWG NO:	G18A2036
SCALE:	NTS	FIGURE 17	
DATE:	09/11/2024		

**Figure 17: 100/200 Amp Meter Pole, Overhead Feeder**



Security Light May Be Leased From The Company. Customer will not be allowed to install their light on this pole.

Pole installed and owned by the Company.

Attachment furnished and installed by the Company.

Weatherhead shall be located no more than 3' below the top of the Pole.

Note:  
Meter Loop will not be installed on Primary Power Poles.

The path to the Service Pole shall be clear of trees and building debris and materials.

Company conductors

A minimum of 24" of wire shall be provided by the Customer. The Neutral shall be marked with white tape. The wire shall be marked or listed as Sunlight Resistant as per NEC 310.10 (D).

Drip-Loop 10' Clearance (Min.) above Finished Grade.

Two Hole Conduit Strap

Service Drop Minimum Clearances	
12'	Above Sidewalks
16'	Above Residential Driveways
18.5'	Above Public Driveways, Alleys, Roads, and Other Areas Subject to Truck & Construction Traffic.

Meter Loop, Meter Socket and Customer's Conduit Will Be Owned And Maintained By The Customer.

Customer's Conduit Will Be Owned And Maintained By The Customer.

Customer supplied and installed Underground Service Feeder. This service feeder will be enclosed in either schedule 80 electrical grade PVC or Rigid Galvanized Steel.

1/0 Copper Ground Wire, This can be insulated and stranded.

4' To 6' above Final Grade Level

30" Recommended Ditch Depth.

5/8" X 8' Copper Clad Steel Ground Rod and Clamp  
Ground Wire and Pole Down Ground are bonded together at the Ground Rod.

Service Size	Wire Sizes Minimum		Conduit Size	Wire Sizes Recommended		Conduit Size	Conduit Type **
	Neutral*	Line		Neutral*	Line		
320 Amp	2-4/0 Cu.	4-4/0 Cu.	3"	2-4/0 Cu.	4-4/0 Cu.	3"	Galv. Rigid Steel
	2-300 AL.	4-300 AL.	4"	2-300 AL.	4-300 AL.	4"	Galv. Rigid Steel

\* Neutral May Be Reduced Under Specific Conditions Allowed By NEC.  
\*\* Other types of conduit allowed depending on local code.


All Equipment Furnished and Installed By Customer Unless Otherwise Noted.



320 Amp Meter Pole, Underground Feeder

REV:	8	DWG NO:	G18A2037
SCALE:	NTS	FIGURE 18	
DATE:	10/25/2024		

Figure 18: 320 Amp Meter Pole, Underground Feeder



**Note:**  
Meter Loop will not be installed on Primary Power Poles.

**Meter Loop, Meter Socket and Customer's Conduit Will Be Owned And Maintained By The Customer.**

Service Drop Minimum Clearances	
12'	Above Sidewalks
16'	Above Residential Driveways
18.5'	Above Public Driveways, Alleys, Roads, and Other Areas Subject to Truck & Construction Traffic.

Service Size	Wire Sizes Minimum		Conduit Size	Wire Sizes Recommended		Conduit Size	Conduit Type **
	Neutral*	Line		Neutral*	Line		
320 Amp	2-4/0 Cu.	4-4/0 Cu.	3"	2-4/0 Cu.	4-4/0 Cu.	3"	Galv. Rigid Steel
	2-300 AL.	4-300 AL.	4"	2-300 AL.	4-300 AL.	4"	Galv. Rigid Steel

\* Neutral May Be Reduced Under Specific Conditions Allowed By NEC.  
\*\* Other types of conduit allowed depending on local code.

**All Equipment Furnished and Installed By Customer Unless Otherwise Noted.**



**320 Amp Meter Pole, Overhead Feeder**

REV:	5	DWG NO:	G18A2038
SCALE:	NTS	FIGURE 19	
DATE:	09/11/2024		

**Figure 19: 320 Amp Meter Pole, Overhead Feeder**

### 6.3 MULTIPLE METERS, SINGLE PHASE OVERHEAD SERVICE

#### A. General Notes:

1. If more than six meters are required, consult the Company for approval of equipment prior to purchase.
2. Service entrance conductors, 5/8" x 8' copper clad steel ground rod, ground rod clamp, ground wire, conduit, conduit straps, weatherhead, lock nuts, bushings, meter socket assembly, meter socket assembly hub, service drop attachment device, and miscellaneous mounting hardware furnished and installed by the Customer.
3. Meters, service connectors, and service drop furnished and installed by Company.
4. The meter socket assembly shall be "readily accessible" (see definitions). The Company requires a level and unobstructed workspace of 78 inches tall, 18 inches on either side, and 48 inches in front of the meter socket assembly. Prior approval is required for placement of the meter socket assembly in alleyways or areas where it may be subject to damage.
5. If the Company is required to attach the service drop directly to the Customer's meter loop conduit, the Customer shall install a steel service mast.
6. The meter sockets shall meet the following specifications:
  - a. The latest revision of U.L. 414 and ANSI C12.7 Standards.
  - b. NEMA 3R compliant enclosure
  - c. Must be U.L. listed.
  - d. Must have grounding connector for triplex.
  - e. Lug size – 2/0 minimum.
  - f. On 120/208v services, the customer must provide the meter socket with 5th lug installed in the 9 o'clock position.
  - g. This is not a complete list of criteria for acceptance. See Appendix A for list of approved meter sockets.**

#### B. Mounting:

1. Meter socket, ground wire, and conduit shall be surface mounted and securely fastened to the structure. The meter socket shall be installed in a level and plumb position. **Flush mounted or recessed metering equipment and service riser conduit embedded in a wall will not be permitted.**
2. Where the exterior wall is other than brick or concrete blocks, a supporting frame shall be installed behind the exterior wall to provide a solid mounting surface for the meter socket.
3. Meter sockets, metering cabinets, and conduit straps shall be installed with the following:
  - a. Lead anchors or double helix concrete screws shall be used with brick or solid concrete surfaces.
  - b. Toggle bolts shall be used with other masonry siding.
  - c. Wood screws shall be used with solid wood surfaces.
  - d. All mounting hardware shall be minimum #12(1/4") corrosion resistant screws.
  - e. A minimum of 4 fasteners shall be used to install any socket or cabinet unless specifically stated otherwise.
4. An intersystem bonding termination bar shall be installed in accordance with NEC 250.94 to facilitate the connection of other utility's ground to a common ground. The location of this device shall be located directly below the meter socket or meter combination socket.
  - a. See Appendix A for list of approved intersystem bonding termination bars.**



C. Connections:

1. The Customer is responsible for termination of the incoming wiring if the wire terminates in a main breaker or fuse holder. The Company will terminate the incoming wire if it terminates on bus bar terminals. The main breaker will be removed when the service wire is being pulled by the Company.
2. Do not score line or load wire when removing insulation.
3. The Customer shall use wire brush or sandpaper to clean all conductors, apply a non-grit type inhibitor, and tighten to manufacturer's specifications.

D. **Meter Socket Marking:**


1. **Before the meters are installed, each socket position and corresponding building unit, i.e., apt number or letter, Suite number or letter, tenant number or letter, or physical address served shall be accurately, clearly, and permanently labeled with an engraved plaque. See Figures 20 and 21 for proper location. Plaques shall be screwed, bolted, or riveted to the equipment. If the equipment is marked incorrectly, the customer shall be responsible for all costs incurred by Liberty for correcting the meter socket identification. Please note that marker ink or adhesive labels are examples of non-permanent labeling.**
2. **Letters or numbers on the engraved plaque shall be a minimum of one (1) inch in height and of contrasting color, i.e., black and white, red and green, orange and blue, etc.**

E. Conductor Marking:

All neutral conductors shall be clearly marked with white tape at the point of delivery and at the meter socket assembly.

Service Size	Wire Sizes		Conduit Size	Wire Sizes		Conduit Size	Conduit Type
	Minimum			Recommended			
	Neutral**	Line		Neutral**	Line		
2-100 Amp	2/0 Cu.	2/0 Cu.	2"	3/0 Cu.	3/0 Cu.	2"	Galv. Rigid Steel
	4/0 AL.	4/0 AL.		250 AL.	250 AL.		
2-200 Amp	2 - 4/0 Cu.	2 - 4/0 Cu.	3"	2 - 4/0 Cu.	2 - 4/0 Cu.	3"	Galv. Rigid Steel
	2 - 300 AL.	2 - 300 AL.		2 - 300 AL.	2 - 300 AL.		

\*\*Neutral may be reduced under specific conditions allowed by NEC



Service Drop Minimum Clearances	
12'	Above Sidewalks
16'	Above Residential Driveways
18.5'	Above Public Driveways, Alleys, Roads, and Other Areas Subject to Truck & Construction Traffic

- NOTES:**
1. If minimum vertical clearance cannot be maintained with the installation of an attachment bolt as shown above, the Customer shall install a Steel Service Mast as shown directly above left.
  2. Connections between Service Drop and Service Entrance Conductors shall be made by Company personnel below Weatherhead, forming a Drip Loop.
  3. Other Types of conduit may be allowed depending on Local Code Requirements. These may include EMT, Electrical Grade (schedule 80) PVC, and Rigid Aluminum. However, the Service Drop shall not be attached to any of these.

**All Equipment Furnished and Installed By Customer Unless Otherwise Noted.**



**Wiring of Two Meters, Overhead Service**

REV:	5	DWG NO:	G18A2039
SCALE:	NTS	FIGURE 20	
DATE:	06/10/2024		

Gang Metering	Ground Wire
2-100 Amp	#4 Cu.
2-200 Amp	1/0 Cu.

**Figure 20: Wiring of Two Meters, Overhead Service**

A minimum of 24" of wire shall be provided. Mark Neutral with white tape. The wire shall be marked or listed as Sunlight Resistant as per NEC 310.10 (D).

The path to the Service Pole shall be clear of trees and building debris and materials.

Company Service Drop & Connectors

Drip-loop 10' clearance (min) above Finished Grade

Insulated Point of Attachment

**The number, type, and size of conduits will vary with each installation. Contact Liberty Utilities for more information.**

Service Drop Minimum Clearances	
12'	Above Sidewalks
16'	Above Residential Driveways
18.5'	Above Public Driveways, Alleys, Roads, and Other Areas Subject to Truck & Construction Traffic

Number of conduits may vary depending on service requirements.

Two Hole Conduit Strap

Line Side Connections

Where the exterior wall is other than brick or concrete blocks, a supporting frame shall be installed behind the exterior wall to provide a solid mounting surface for the metering equipment.


**No Bypass Lever Allowed.**

\* Provision for Company seal and company padlock with 3/8" shackle.

☒☒☒ Marking as required in Section 6.3.D.

✓ Unit disconnection means lock-off provisions must accept Company padlock with 3/8" shackle.

Either install a #6 copper wire (Minimum) from the same connection point as the main Copper Ground Wire connection in the multi-meter incoming compartment or the ground rod to Intersystem Ground Connector.



4' - 6' above Final Grade

Main Copper Ground Wire as per NEC. This wire shall be external and attached to the building. Follow NEC Guidelines if conduit is used.

A minimum of one 5/8" X 8' Copper Clad Steel Ground Rod shall be provided by Customer. However, more than one Ground Rod may be needed. Consult NEC for requirements.

All Grounding Systems shall be bonded together.

**Notes:**

1. If minimum vertical clearance cannot be maintained with the installation of an attachment point as shown above, contact the Company for requirements.
2. Connections between Service Drop and Service Entrance Conductors shall be made by Company personnel below Weatherhead, forming a Drip Loop.
3. Service Entrance Conductors shall be sized as per NEC

**If more than 6 meters are required, please contact the Company for configuration. As a minimum, Liberty Utilities will require the riser diagram and cut sheets as proposed by the Electrical Engineer.**

**All Equipment Furnished and Installed By Customer Unless Otherwise Noted.**



Three to Six Meters, Overhead Service

REV:	5	DWG NO:	G18A2040
SCALE:	NTS	FIGURE 21	
DATE:	06/11/2024		

Figure 21: Three to Six Meters, Overhead Service

## 7.0 UNDERGROUND SERVICES

### 7.1 GENERAL INFORMATION

1. PLEASE CONTACT THE COMPANY BEFORE PLANNING FOR AN UNDERGROUND SERVICE.

2. MINIMUM CLEARANCES OF SERVICE LATERALS IN CONDUIT

Horizontal from gas, water, and sewer lines.....5 feet


Horizontal from telephone or cable television lines.....1 foot

Horizontal to any structures (including footings and foundations).....5 feet

Horizontal from conductor to edge of swimming pool or its auxiliary equipment (Applies to above or in ground swimming pools).....10 feet

*Note: If within ten feet of service point, this clearance does not apply to structures served.*

3. Help avoid the need for future trimming by planting trees and shrubs in the right place.



4. The service lateral shall not cross a sewer lateral field.


5. **The Customer shall request the Company to designate the location of the point of delivery for each service location before construction is started.**

6. Before doing any excavation, contact all Utilities to locate their underground facilities. The following are the One Call numbers for each state listed.

Missouri	(800) 344 – 7483
Kansas	(800) 344 – 7233
Arkansas	(800) 482 – 8998
Oklahoma	(800) 522 – 6543

7. The Customer will be held responsible to locate and mark all privately owned (Customer's or others) underground facilities.

8. Guard Posts maybe required on any underground service installation to protect the Company's Equipment. Contact the Company for requirements.



**Caution!**  
Contact all Utilities  
before digging


**NOTES:**

1. Backfill shall be compacted with the wheels of the excavation equipment or by other suitable means prior to final backfilling. The top of the backfilled trench shall be approximately level with the surrounding grade. Excess soil shall be hauled away. Final backfilling and cleanup shall not be done during adverse weather conditions.
2. An area on each side of the trench will be disturbed by the trenching, backfilling and cleanup operations. The area shall be leveled with the surrounding grade and cleanup, and it is the responsibility of the property owner to replant it with grass and to do any future landscaping that might be needed.

**Ditch Profile**

Service is provided as line of sight from Meter Socket location to service source. If the service route differs from this due to obstructions or terrain or is longer than 100 feet, **contact Liberty for requirements. Additional cost may apply.**

The Company will provide and install the conduit system for a fee from a point four foot away from the structure.



**!!!! WARNING !!!!**  
If this elbow is not supported or if the soil under it is not well compacted, the conduit may pull out of the meter socket resulting in a possible failure of the service.

**DO NOT USE WHITE WATER PIPE.**

This denotes undisturbed earth.

**If the Customer digs the ditch, a Ditch Inspection is REQUIRED. Contact the Company to schedule an inspection.**

02/04/21	DER
06-21-19	KMH
04-01-09	SDS
05-17-05	SDS
REVISIONS	




Underground Service Detail	
DRAWN: SDS	DWG. NO. G18A2041
SCALE: NTS	FIGURE 22
DATE: 06/06/03	

Figure 22: Underground Service Detail


**Caution !  
Contact all Utilities  
before digging**

**The Company will provide and install the conduit system  
for a fee from a point four foot away from the structure.**




**Service is provided as line of sight from Meter Socket location to  
service source. If the service route differs from this due to  
obstructions or terrain or is longer than 100 feet, contact Liberty  
for requirements. Additional cost may apply.**

**The Company will provide and install the conduit system  
for a fee from a point four foot away from the structure.**



**!!!! WARNING !!!!**  
If this elbow is not supported or if the soil under it is not well compacted, the conduit may pull out of the meter socket resulting in a possible failure of the service.

 This denotes undisturbed earth.

**If the Customer digs the ditch, a Ditch Inspection is REQUIRED. Contact the Company to schedule an inspection.**

02/04/21	DER
07-10-19	KMH
04-01-09	SDS
	REVISIONS




Underground Service Detail (Continued)	
DRAWN: SDS	DWG. NO. G18A2042
SCALE: NTS	FIGURE 23
DATE: 07/15/06	

Figure 23: Underground Service Detail (Continued)



**Service Equipment shall be installed as shown in these Service Standards. Install this equipment on front side of this structure.**

Larger structure may be permitted with submission of wind study. Contact the Company.



**Contact Liberty Utilities for location, orientation, and/or verification before installing this structure.**

**Caution!  
Contact all Utilities  
before digging**

**All Equipment Furnished & Installed By Customer Unless Otherwise Noted.**




Underground Service Structure

REV:	2	DWG NO:	G18A2043
SCALE:	NTS	FIGURE 24	
DATE:	06/11/2024		

**Figure 24: Underground Service Structure**

**Service Equipment shall be installed as shown in these Service Standards. Install this equipment on front side of this structure.**



**Contact Liberty Utilities for location, orientation, and/or verification before installing this structure.**

**Caution!**  
**Contact all Utilities before digging**

**All Equipment Furnished & Installed By Customer Unless Otherwise Noted.**



Small Underground Service Structure

REV:	0	DWG NO:	G18A2056
SCALE:	NTS	FIGURE 25	
DATE:	06/11/2024		

**Figure 25: Small Underground Service Structure**



## 7.2 200 AMP AND 320 AMP SINGLE PHASE UNDERGROUND SERVICE

### A. General Notes:

1. Service entrance conductors, 5/8" x 8' copper clad steel ground rod, ground rod clamp, ground wire, conduit, conduit straps, lock nuts, bushings meter socket, hub closing plate, and miscellaneous mounting hardware furnished and installed by Customer.
2. Meter and service lateral conductors furnished and installed by Company.
3. The meter socket shall be "readily accessible" (see definitions). The Company requires a level and unobstructed workspace of 78 inches tall, 18 inches on either side, and 48 inches in front of the meter socket. Prior approval is required for placement of the meter socket in alleyways or areas where it may be subject to damage.
4. The 200 amp and 320 amp meter sockets shall meet the following specifications:
  - a. The latest revision of U.L. 414 and ANSI C12.7 Standards.
  - b. NEMA 3R compliant enclosure
  - c. Must be U.L. listed.
  - d. Must have grounding connector for triplex.
  - e. Lug size – 2/0 minimum.
  - f. On 120/208v services, the customer must provide the meter socket with 5th lug installed in the 9 o'clock position.
  - g. This is not a complete list of criteria for acceptance. See Appendix A for list of approved meter sockets.**
5. Conduit system shall be installed as per Figure 22 or 23.

### B. Mounting:

1. Meter socket, ground wire, and conduit shall be surface mounted and securely fastened to the exterior structure. The meter socket shall be installed in a level and plumb position. **Flush mounted or recessed metering equipment and service lateral conduit embedded in a wall will not be permitted.**
2. Where the exterior wall is other than brick or concrete blocks, a frame shall be installed behind the exterior wall to provide a solid mounting surface for the meter socket.
3. Meter sockets, metering cabinets, and conduit straps shall be installed with the following:
  - a. Lead anchors or double helix concrete screws shall be used with brick or solid concrete surfaces.
  - b. Toggle bolts shall be used with other masonry siding.
  - c. Wood screws shall be used with solid wood surfaces.
  - d. All mounting hardware shall be minimum #12(1/4") corrosion resistant screws.
  - e. A minimum of 4 fasteners shall be used to install any socket or cabinet unless specifically stated otherwise.
4. An intersystem bonding termination bar shall be installed in accordance with NEC 250.94 to facilitate the connection of other utility's ground to a common ground. The location of this device shall be located directly below the meter socket or meter combination socket.
  - a. See Appendix A for list of approved intersystem bonding termination bars.**

5. If PVC is used for the conduit attached to the meter socket, the rigid metal elbow shall be grounded/bonded to the service ground rod unless it is isolated from possible contact by a minimum cover of 18 inches to any part of the elbow as per NEC Article 250.80, Service Raceways and Enclosures.

**a. See Appendix A for list of approved grounding clamps.**

6. For 200 amp service, a minimum of two inch (2") galvanized rigid steel or electrical grade Schedule 80 PVC conduit shall be furnished and installed by Customer as shown in Figure 25.

7. For 320 amp service, a minimum of three inch (3") galvanized rigid steel or electrical grade Schedule 80 PVC conduit shall be furnished and installed by Customer as shown in Figure 25.

C. Connections:

1. Do not score load wire when removing insulation.

2. The Customer shall use wire brush or sandpaper to clean all conductors, apply a non-grit type inhibitor and tighten to manufacturer's specifications.

D. Conductor Marking:

All neutral conductors shall be clearly marked with white tape at the meter socket.

**Ground Rod and Wire MUST be Installed and Ground Wire MUST be attached to the structure before Service will be Connected.**

200 amp Meter Socket and Disconnect or 200 amp combination meter socket shall be furnished **by the Customer**. When a disconnect is used, it shall be not be closer than 1" nor farther away than 1' from the meter socket. Disconnects are required on the 320 amp meter socket and shall be located on the exterior of the structure. If more than one disconnect is required, they shall all be placed at the same location. A 200 amp combination socket is shown. Emergency disconnects shall be installed in accordance with NEC 230.85

Meter furnished and installed **by Company**

Bypass Lever allowed on 320 amp meter socket only.

Install Intersystem Ground Connector


Slip-Joint may be used if permissible by local jurisdiction.

Service Size	Ground Wire
200 Amp	#4 Cu.
320 Amp	1/0 Cu.

This wire shall be external and attached to the building. Follow NEC Guidelines if Conduit is used


Service Size	Conduit Size	Recommended Conduit Type
200 Amp	2"	Galvanized Rigid Steel
320 Amp	3"	Galvanized Rigid Steel

Note: Sch 80 electrical grade PVC may be used.



4' to 6' Above Final Grade Level

30" (Min) Ditch Depth



**Sweep ell min. radius**

Conduit Size	Radius
2"	9.5"
3"	13"

Note: Galvanized Rigid Steel

**Preferred**

**Alternate**

**Caution!**  
**Contact all Utilities before digging**

**!!!! WARNING !!!!**

If this elbow is not supported or if the soil under it is not well compacted, the conduit may pull out of the meter socket resulting in a possible failure of the service.



This denotes undisturbed earth.

**Notes:**

1. If a conduit reducer is used, it must be located immediately below the Meter Socket.
2. Line of Sight installation is required. See Definitions.
3. A conduit vent may be needed depending on the service arrangement and terrain.
4. If the service route is longer than 100 feet, contact Liberty Utilities for conduit requirements.
5. A metal elbow that is installed in an underground installation of rigid nonmetallic conduit and is isolated from possible contact by a minimum cover of 18 inches to any part of the elbow shall not be required to be grounded as per NEC Article 250.80, Service Raceways and Enclosures.


**All Equipment Furnished & Installed By Customer Unless Otherwise Noted.**



**200/320 Amp Underground Service**

REV:	6	DWG NO:	G18A2044
SCALE:	NTS	FIGURE 26	
DATE:	06/11/2024		

**Figure 26: 200/320 Amp Underground Service**



**All Equipment Furnished and Installed By Customer Unless Otherwise Noted.**




**200 Amp Meter Socket, Underground Service**

REV:	6	DWG NO:	G18A2045
SCALE:	NTS	FIGURE 27	
DATE:	06/11/2024		

**Figure 27: 200 Amp Meter Socket, Underground Service**

**Note:**  
**This application for 120/208v, 3 wire service.**




**All Equipment Furnished and Installed By Customer Unless Otherwise Noted.**



200 Amp Meter Socket,  
 Network (120/208),  
 Underground Service

REV:	5	DWG NO:	G18A2046
SCALE:	NTS	FIGURE 28	
DATE:	06/11/2024		

**Figure 28: 200 Amp Meter Socket, Network (120/208), Underground Service**



**DO NOT Install Multiple Conductors Under One Lug.**

**DO NOT Install Multiple Conductors Under One Lug.**

**No Bypass Lever Allowed.**

Energized parts of service equipment shall be enclosed or guarded in accordance with NEC 230.62

If a Hub Plate or Meyer's Hub is not used, a Protective Bushing is required for PVC or if Rigid Steel is used, a Grounding Bushing is required.

Protective Bushing

Neutral shall be marked with white tape at the Meter Socket.

**Note:**

No center installation of conduit allowed. Conduit furnished and installed **by Customer** in the left or right bottom knockout provided.

**All Equipment Furnished and Installed By Customer Unless Otherwise Noted.**



200 Amp Combination, Meter Socket, Underground Service

REV:	4	DWG NO:	G18A2047
SCALE:	NTS	FIGURE 29	
DATE:	06/11/2024		

Figure 29: 200 Amp Combination Meter Socket, Underground Service



**Note:**

**This application for 120/208v, 3 wire service.**

The Customer will provide and install the 5th lug on **Approved Meter Sockets**. For a list of these, refer to **Appendix A**.

This wire must have white insulation and will be connected as shown. This wire will be provided and installed by the Customer on **Approved Meter Sockets**.

Energized parts of service equipment shall be enclosed or guarded in accordance with NEC 230.62

**DO NOT Install Multiple Conductors Under One Lug.**

If a Hub Plate or Meyer's Hub is not used, a Protective Bushing is required for PVC or if Rigid Steel is used, a Grounding Bushing is required.

Neutral shall be marked white tape at the Meter Socket.

**Note:**


No center installation of conduit allowed. Conduit furnished and installed **by Customer** in the left or right bottom knockout provided.

**All Equipment Furnished and Installed By Customer Unless Otherwise Noted.**




200 Amp Combination Meter Socket Network (120/208), Underground Service

REV:	5	DWG NO:	G18A2048
SCALE:	NTS	FIGURE 30	
DATE:	06/11/2024		



**Figure 30: 200 Amp Combination Meter Socket, Network (120/208), Underground Service**



**All Equipment Furnished & Installed By Customer Unless Otherwise Noted.**



**320 Amp Meter Socket  
Underground Service**

REV:	6	DWG NO:	G18A2049
SCALE:	NTS	FIGURE 31	
DATE:	06/11/2024		

**Figure 31: 320 Amp Meter Socket, Underground Service**



**Note:**

**This application for 120/208v, 3 wire service.**


This wire must have white insulation and will be connected as shown. This wire will be provided and installed by the Customer on **Approved Meter Sockets**.

The Customer will provide and install the 5th lug on **Approved Meter Sockets**. For a list of these, refer to **Appendix A**.

**Ground Connector**  
The Ground Wire shall not be carried through this connector to the Main Panel.

Neutral shall be marked with white tape at the Meter Socket.

**DO NOT Install Multiple Conductors Under One Lug.**



**All Equipment Furnished & Installed By Customer Unless Otherwise Noted.**




320 Amp Meter Socket,  
Network (120/208),  
Underground Service

REV:	2	DWG NO:	G18A2049A
SCALE:	NTS	FIGURE 31A	
DATE:	06/11/2024		

**Figure 31A: 320 Amp Meter Socket, Network (120/208), Underground Service**

Label disconnect as required by NEC

RESIDENTIAL



**DO NOT Install Multiple Conductors Under One Lug Without Approval From The Company**

If a Hub Plate or Myers Hub is not used, a Protective Bushing is required for PVC or if Rigid Steel is used, a Grounding Bushing is required.

**All Equipment Furnished and Installed By Customer Unless Otherwise Noted.**



**320 Amp Combination Meter Socket  
Underground Service**


REV:	2	DWG NO:	G18A2050
SCALE:	NTS	FIGURE 32	
DATE:	06/11/2024		

**Figure 32: 320 Amp Combination Meter Socket, Underground Service**

Label disconnect as required by NEC

RESIDENTIAL

**Note:**  
This application for  
120/208v, 3 wire service.



**All Equipment Furnished and Installed By Customer Unless Otherwise Noted.**



320 Amp Combination Meter Socket, Network (120/208), Underground Service


REV:	2	DWG NO:	G18A2050A
SCALE:	NTS	FIGURE 32A	
DATE:	06/11/2024		

Figure 32A: 320 Amp Combination Meter Socket, Network (120/208), Underground Service


**Caution!**  
**Contact all utilities**  
**before digging**

**Meter Pedestal leased for a fee.**  
 The company will own, install, and maintain the pedestal.

**Service in Conduit**



**Mobile home parks can only be served 120/240 1Ø as per NEC 550.30.**

 Liberty			Meter Pedestal	
			REV: 5	DWG NO: G18A2051
SCALE: NTS		FIGURE 33		
DATE: 06/11/2024				

**Figure 33: Meter Pedestal**

### 7.3 600 AMP TO 800 AMP CT METERING, SINGLE PHASE UNDERGROUND SERVICE

#### A. General Notes:

1. This arrangement may be utilized for services above 320 amps (continuous) and less than or equal to 800 amps.
2. The service lateral conductors and meter are furnished and installed by the Company. Customer will provide approximate final grade level within six inches (6") prior to service lateral installation.
3. The current transformers (CT) are furnished and installed by the Company.  
**The Customer shall provide and install the CT/connection cabinet.**
  - a. **See Appendix A for list of approved CT/connection cabinets.**
4. The meter socket shall be purchased from the Company and installed by the Customer. The location of this CT Cabinet and Meter will be determined by Liberty.
5. The metering control cable is furnished and installed by the Company.
6. The metering equipment should be "readily accessible" (see definitions). The Company requires a level and unobstructed workspace of 78 inches tall, 18 inches on either side, and 48 inches in front of the metering equipment. Prior approval is required for placement of the metering equipment in alleyways or areas where it may be subjected to damage.

#### B. Mounting:

1. Meter socket, ground wire, CT/connection cabinet, and conduits for service lateral and metering control cable shall be surface mounted and securely fastened to the structure. The meter socket shall be installed in a level and plumb position. **Flush mounted or recessed metering equipment and service lateral conduit embedded in a wall will not be permitted.**
2. Where the exterior wall is other than brick or concrete blocks, a support frame shall be installed behind the exterior wall to provide a solid mounting surface for the metering equipment.
3. Meter sockets, metering cabinets, and conduit straps shall be installed with the following:
  - a. Lead anchors or double helix concrete screws shall be used with brick or solid concrete surfaces.
  - b. Toggle bolts shall be used with other masonry siding.
  - c. Wood screws shall be used with solid wood surfaces.
  - d. All mounting hardware shall be minimum #12(1/4") corrosion resistant screws.
  - e. A minimum of 4 fasteners shall be used to install any socket or cabinet unless specifically stated otherwise.
4. An intersystem bonding termination bar shall be installed in accordance with NEC 250.94 to facilitate the connection of other utility's ground to a common ground. The location of this device shall be located directly below the meter socket or meter combination socket.
  - a. **See Appendix A for list of approved intersystem bonding termination bars.**

5. If PVC is used for the conduit attached to the meter socket, the rigid metal elbow shall be grounded/bonded to the service ground rod unless it is isolated from possible contact by a minimum cover of 18 inches to any part of the elbow as per NEC Article 250.80, Service Raceways and Enclosures.

**a. See Appendix A for list of approved grounding clamps.**

6. Conduits shall be furnished and installed by Customer.

C. Connections:

All connections inside the CT/connection cabinet shall be made by the Company. The Company shall provide the connectors.


D. Conductor Marking:

All neutral conductors shall be clearly marked with colored tape at the point of delivery.

**THIS PAGE INTENTIONALLY LEFT BLANK**



**Caution!**  
**Contact all utilities**  
**before digging**



**NOTE:**  
**Customer's**  
**Service**  
**Entrance**  
**Conductors**  
**shall extend**  
**48 inches**  
**inside cabinet**

**NOTES:**

1. A 1/4" synthetic pull rope must be installed in the conduit.
2. A conduit vent may be needed depending on the service arrangement and terrain.
3. Line of Sight installation is required. See Definitions.
4. If the service route is longer than 100', contact the company for conduit requirements.
5. A metal elbow that is installed in an underground installation of rigid nonmetallic conduit and is isolated from possible contact by a minimum cover of 18 inches to any part of the elbow shall not be required to be grounded as per NEC Article 250.80, Service Raceways and Enclosures.
6. The Main Disconnecting means can not consist of more than six individual disconnects in combination. These shall all be located external to the building and at one location at the metering point.

**!!!! WARNING !!!!**  
 If this elbow is not supported or if the soil under it is not well compacted, the conduit may pull out of the CT Cabinet resulting in a possible failure of the service.

**All Equipment Furnished & Installed By Customer Unless Otherwise Noted.**



**600 Amp to 800 Amp Current Transformer Metering, Underground Service**

REV:	6	DWG NO:	G18A2052
SCALE:	NTS	FIGURE 34	
DATE:	06/11/2024		

**Figure 34: 600 Amp to 800 Amp, Current Transformer Metering, Underground Service**



## 7.4 MULTIPLE METERS, SINGLE PHASE UNDERGROUND SERVICE

### A. General Notes:

1. If more than six meters are required, consult the Company for approval of equipment prior to purchase.
2. Service entrance conductors, 5/8" x 8' copper clad steel ground rod, ground rod clamp, ground wire, conduit, conduit straps, lock nuts, bushings, meter socket assembly, hub closing plate, and miscellaneous mounting hardware furnished and installed by the Customer.
3. Meters, service connectors, and service lateral conductors furnished and installed by Company.
4. The meter socket assembly should be "readily accessible" (see definitions). The Company requires a level and unobstructed workspace of 78 inches tall, 18 inches on either side, and 48 inches in front of the meter socket assembly. Prior approval is required for placement of the meter socket assembly in alleyways or areas where it may be subjected to damage.
5. The 100 Amp and 200 Amp meter sockets shall meet the following specifications:
  - a. The latest revision of U.L. 414 and ANSI C12.7 Standards.
  - b. NEMA 3R compliant enclosure
  - c. Must be U.L. listed.
  - d. Must have grounding connector for triplex.
  - e. Lug size – 2/0 minimum.
  - f. On 120/208v services, the customer must provide the meter socket with 5th lug installed in the 9 o'clock position.
  - g. This is not a complete list of criteria for acceptance. See Appendix A for list of approved meter sockets.**

### B. Mounting:

1. Meter socket assembly, ground wire, and conduit shall be surface mounted and securely fastened to the structure. The meter socket assembly shall be installed in a level and plumb position. **Flush mounted metering or recessed equipment and service lateral conduit embedded in a wall will not be permitted.**
2. Where the exterior wall is other than brick or concrete blocks, a support frame shall be installed behind the exterior wall to provide a solid mounting surface for the meter socket.
3. Meter sockets, metering cabinets, and conduit straps shall be installed with the following:
  - a. Lead anchors or double helix concrete screws shall be used with brick or solid concrete surfaces.
  - b. Toggle bolts shall be used with other masonry siding.
  - c. Wood screws shall be used with solid wood surfaces.
  - d. All mounting hardware shall be minimum #12(1/4") corrosion resistant screws.
  - e. A minimum of 4 fasteners shall be used to install any socket or cabinet unless specifically stated otherwise.
4. An intersystem bonding termination bar shall be installed in accordance with NEC 250.94 to facilitate the connection of other utility's ground to a common ground. The location of this device shall be located directly below the meter socket or meter combination socket.
  - a. See Appendix A for list of approved intersystem bonding termination bars.**

5. If PVC is used for the conduit attached to the meter socket, the rigid metal elbow shall be grounded/bonded to the service ground rod unless it is isolated from possible contact by a minimum cover of 18 inches to any part of the elbow as per NEC Article 250.80, Service Raceways and Enclosures.

**a. See Appendix A for list of approved grounding clamps.**

6. Conduit ends shall be equipped with a proper bushing to protect the conductors.

**C. Connections:**

1. The Customer is responsible for termination of the incoming wiring if the wire terminates in a main breaker or fuse holder. The Company will terminate the incoming wire if it terminates on bus bar terminals. The main breaker will be removed when the service wire is being pulled by the Company.

2. Do not score load wire when removing insulation.

3. The Customer shall use wire brush or sandpaper to clean all conductors, apply a non-grit type inhibitor and tighten to manufacturer's specifications.

**D. Meter Socket Marking:**

1. **Before the meters are installed, each socket position and corresponding building unit, i.e., apt number or letter, Suite number or letter, tenant number or letter, or physical address served shall be accurately, clearly, and permanently labeled with an engraved plaque. See the Figures 35, 36, and 37 for proper location. Plaques shall be screwed, bolted or riveted to the equipment. If the equipment is marked incorrectly, the customer shall be responsible for all costs incurred by Liberty for correcting the meter socket identification. Please note that marker ink or adhesive labels are examples of non-permanent labeling.**

2. **Letters or numbers on the engraved plaque shall be a minimum of one (1) inch in height and contrasting color, i.e., black and white, red and green, orange and blue, etc.**

**E. Conductor Marking:**


All neutral conductors shall be clearly marked with white tape at the meter socket assembly.

**Caution!**  
Contact all utilities  
before digging



The maximum amperage  
Meter Socket allowed in  
this configuration is 200A.

- \* Provision for Company seal and Company padlock with 3/8" shackle
- ☒☒☒ Marking as required in Section 7.4.D
- ✓ Unit disconnection means with lock-off provisions must accept Company padlock with 3/8" shackle

The maximum amperage  
Meter Socket allowed in  
this configuration is 200A.



Gang Metering	Ground Wire
2-100 Amp	#4 Cu
2-200 Amp	#2 Cu



Sweep Ell Minimum Radius	
Conduit Size	Radius
2"	9.5"
3"	13"

Note: Galvanized Rigid Steel

**Preferred**

**Alternate**

**!!!! WARNING !!!!**  
If this elbow is not supported or if the soil under it is not well compacted, the conduit may pull out of the Meter Pack resulting in a possible failure of the service.

☒☒☒ This denotes undisturbed earth.

**NOTES:**

1. A Conduit Vent may be needed depending on the service arrangement and terrain.
2. Line of Sight installation is required. See Definitions.
3. If the service route is longer than 100', contact the Company for conduit requirements.
4. A metal elbow that is installed in an underground installation of rigid nonmetallic conduit and isolated from possible contact by a minimum cover of 18 inches to any part of the elbow shall not be required to be grounded as per NEC Article 250.80, Service Raceways and Enclosures.
5. A 1/4" synthetic pull rope must be installed in the conduit.

**All Equipment Furnished & Installed By Customer Unless Otherwise Noted.**



**Wiring of Two Meters Underground Service**

REV:	5	DWG NO:	G18A2053
SCALE:	NTS	FIGURE 35	
DATE:	06/11/2024		

**Figure 35: Wiring of two Meters, Underground Service**

The maximum amperage Meter Socket allowed in this configuration is 200A.

\* Provision for company seal and company padlock with 3/8" shackle

☒☒☒ Marking as required in Section 7.4.D

✓ Unit disconnection means with lock-off provisions must accept company padlock with 3/8" shackle

**No Bypass Lever Allowed.**

Slip-Joint may be used if permissible by local jurisdiction.

Rigid steel conduit is preferred but Sch 80 electrical grade PVC may be used. Number and size of conduits may vary depending on service requirements. Contact the Company for details.

Copper ground wire as per NEC. This wire shall be external and attached to the building. Follow NEC Guidelines if Conduit is used.

The maximum amperage Meter Socket allowed in this configuration is a 200A.

4' - 6' above Final Grade

Install a #6 copper wire (MIN) from the same connection point as the main Copper Ground Wire connection through the Intersystem Ground Connector to the ground rod.

30" (MIN) to the bottom of ditch

**All Grounding Systems shall be bonded together.**

A minimum of one 5/8" X 8' Copper Clad Steel Ground Rod shall be provided by Customer. However, more than one ground rod may be needed. Consult NEC for requirements.

The conduits shall rest on the bottom of the trench and will point toward the service source. See Figure 22 & 23.

Galvanized Rigid Steel Ground elbow with grounding clamp See Note 4.

☒☒☒ This denotes undisturbed earth.

**!!!! WARNING !!!!**  
If this elbow is not supported or if the soil under it is not well compacted, the conduit may pull out of the Meter Pack resulting in a possible failure of the service.

**The number, type, and size of conduits will vary with each installation. Contact the Company for more information.**

**Caution!**  
**Contact all utilities before digging**

**If more than 6 meters are required, please contact the Company for configuration. As a minimum, Liberty Utilities will require the riser diagram and cut sheets as proposed by the Electrical Engineer.**

**NOTES:**

1. A Conduit Vent may be needed depending on the service arrangement and terrain.
2. Line of Sight installation is required. See Definitions.
3. If the service route is longer than 100', contact the Company for conduit requirements.
4. A metal elbow that is installed in an underground installation of rigid nonmetallic conduit and isolated from possible contact by a minimum cover of 18 inches to any part of the elbow shall not be required to be grounded as per NEC Article 250.80, Service Raceways and Enclosures.
5. A 1/4" synthetic pull rope must be installed in the conduit.

**All Equipment Furnished & Installed By Customer Unless Otherwise Noted.**




Three to Six Meters, Underground Service

REV:	6	DWG NO:	G18A2054
SCALE:	NTS	FIGURE 36	
DATE:	06/11/2024		

Figure 36: Three to Six Meters, Underground Service

**THIS PAGE INTENTIONALLY LEFT BLANK**

- \* Provision for company seal and company padlock with 3/8" shackle
- ☒☒☒ Marking as required in Section 7.4.D
- ✓ Unit disconnection means with lock-off provisions must accept company padlock with 3/8" shackle



Slip-Joint may be used if permissible by local jurisdiction.

Rigid steel conduit is preferred but Sch 80 electrical grade PVC may be used.

Bypass Lever allowed on 320 amp meter socket only.

Install a #6 copper wire (Minimum) from the same connection point as the main Copper Ground Wire connection through the Intersystem Ground Connector to the ground rod.

6' (MAX) above Final Grade

2.5' (MIN) above Final Grade

FINAL GRADE

The number and size of conduits will vary with each installation. refer to other sections in this document for conduit placement. Contact the Company for more information for answers to other questions concerning conduit systems.

A minimum of one 5/8" X 8' Copper Clad Steel Ground Rod shall be provided by Customer. However, more than one ground rod may be needed. Consult NEC for requirements.

Service Equipment Ground Electrode System as per NEC furnished and installed by Customer.

Copper ground wire as per NEC. This wire shall be external and attached to the building. Follow NEC Guidelines if conduit is used.

**Caution!**  
Contact all utilities before digging

**Notes:**

1. A conduit vent may be needed depending on the service arrangement and terrain.
2. Line of Sight installation is required. See Definitions.
3. If the service route is longer than 100', contact the Company for conduit requirements.
4. A metal elbow that is installed in an underground installation of rigid nonmetallic conduit and is isolated from possible contact by a minimum cover of 18 inches to any part of the elbow shall not be required to be grounded as per NEC Article 250.80.
5. A 1/4" synthetic pull rope must be installed in the conduit.
6. If service is supplied from a three phase source, load must be balanced across all phases.

If more than 6 meters are required, please contact the Company for configuration. As a minimum, Liberty Utilities will require the riser diagram and cut sheets as proposed by the Electrical Engineer.

**All Equipment Furnished & Installed By Customer Unless Otherwise Noted.**



Seven or More Meters, Underground Service

REV:	1	DWG NO:	G18A2055
SCALE:	NTS	FIGURE 37	
DATE:	06/11/2024		

Figure 37: Seven or More Meters, Underground Service

## **Appendix A**

**Note: Please seek approval from the Company prior to purchasing equipment not listed in this Appendix.**

**Note: Additional equipment such as surge arresters may be required according to NEC requirements. The Company does not take responsibility for making this determination when approving equipment.**

### **Residential – Approved Equipment Examples**

#### **Individual Meter Sockets – Overhead**

<b>Service Size</b>	<b>Eaton</b>	<b>Durham</b>	<b>Milbank</b>	<b>Talon</b>	<b>Square D</b>	<b>Eaton B-Line</b>	<b>Midwest</b>
100A	UTRS101BE UTRS111BCH URTRS101BE	UT-RS101B UT-RS111B URT-RS101B URT-RS111B	U7487-RL-TG U7490-RL-TG	UAT111-0G UAT121-0G	UTRS101B URTRS101B	011 011 MS73	UTRS101BMEP
200A	UTRS202BCH UTRS212BCH UTRS213BE URTRS202BCH URTRS213BE	UT-RS202B UT-RS213B URT-RS202B URT-RS213B	U7017-RL-TG U7021-RL-TG U7040-RL-TG	UAT317-0G UAT327-0G UAT417-0G UAT427-0G	UTRS202B UTRS213B	204	UTRS202BMEP UTRS213BMEP
300A	UTH4330UCH + ARP00427CH	UT-H4309T	U4702-X-2/K2	47704-01 + (2)H56732	UTH4330T + ARP00427 1008068		UTH4300TFLMEP + Lugs 1007672MEP

### Individual Meter Sockets – Overhead (5th Lug)

Service Size	Eaton	Durham	Milbank	Talon	Square D	Eaton B-Line	Midwest
100A	UGHTRS101BCH UGHTRS111BCH 1003880ACH	UGT-RS101B UGT-RS111B UGRT-RS101B UGRT-RS111B	U7487-RL-TG-5T9 U7490-RL-TG-5T9	UAT111-0BG UAT121-0BG	UTRS101B + A5J URTRS101B + A5J UGHTRS101B	011 + MSR5TK	UGHTRS101BMEP UTRS101BMEP + MS5
200A	UGTRS202BCH UGTRS213BE UGTRS212BCH	UGT-RS202B UGT-RS213B UGRT-RS202B UGRT-RS213B	U7017-RL-TG-5T9 U7021-RL-TG-5T9 U7040-RL-TG-5T9	UAT317-0BG UAT327-0BG UAT417-0BG UAT427-0BG	URS202BCR UTRS202B + A5J UTRS213B + A5J	204 + 50365	UGHTRS213BMEP UTRS202BMEP + MS5 UTRS213BMEP + MS5
300A	UTH4330UCH + ARP00427CH + ARP00862CH	UGT-H4309T	U4505-X-2/K2 U4702-X-5T9-2/K2	47704-01 + (2)H56732 + H35815-2			UTH4300FLMEP + Lugs + MS5 1007672MEP + MS5

### Combination Meter Sockets – Overhead

Service Size	Eaton	Durham	Milbank	Talon	Square D	Eaton B-Line	Midwest
100A	MB816P200BTS* CMBP200BTS* MBP200BTS*	UH122N0B	U5168-XTL-100 U5169-XTL-100 U3499-XL-TG-100 U5842-RL-TG-100 U5844-PXL-TG-100	MM0202ML1100S* MC0816B1200CT*	SC8L125S + breakers SC1624M125S + breakers	1M1R	M101CB2 R101CB2ETG
200A	MB816B200BTS MB48B200BTS MBB200BTS MBB200BTSC CMBB200BTS* MBP200BTS* MBT48B200BTS	UC222W1B UDC222W1B UDRC222W1B UC242W1B-S UC262W1B-S P2102D1C-SV	U5842-RL-TG-200 U5844-PXL-TG-200 U5168-XTL-200 U5169-XTL-200 U5842-RL-TG-200 U5844-PXL-TG-200	LG0408B1200RT LG0816B1200RCT MM0202B1200 MM0202B1200R MC0816B1200CT	SC12L200S + breakers SC2040M200 C + Breakers	2M2R	M208CR2A R208CR2A R208CR2AETG
300A		UHC344N3T-C	U6601-X-TG-2/200 U6604-X-TG-2/200	MK0402L1400RLM + (2)QN2200RH MK0402L1400SC + (2)QN2200RH			MS45508C RS45500C

\* To provide 100A service, this socket will be installed and a separate Customer supplied 100A breaker will be installed to supply the 100A service.



### Combination Meter Sockets – Overhead (5th Lug)

Service Size	Eaton	Durham	Milbank	Talon	Square D	Midwest
100A	MB816P200BTS* + MB5JAWKIT CMBP200BTS* + MB5JAWKIT MBP200BTS* + MB5JAWKIT MB816B200STD*	UH122N0B + ARP00035	U5168-XTL-100-5T9 U5169-XTL-100-5T9 U3499-XL-TG-100-5T9 U5842-RL-TG-100-5T9 U5844-PXL-TG-100-5T9	MC0816B1200CT* + EC5J2	SC8L125S + Breakers + 5j SC1624M125S + Breakers + 5J	M101CB2 + ARP00035MEP R101CB2ETG + ARP00035MEP
200A	MB816B200BTS + MB5JAWKIT MB48B200BTS + MB5JAWKIT MBB200BTS + MB5JAWKIT MBB200BTSC + MB5JAWKIT CMBB200BTS + MB5JAWKIT MBP200BTS + MB5JAWKIT MB816B200STD	UC222W1B + ARP00035 UDC222W1B + ARP00035 UC242W1B-S + ARP00035 UC262W1B-S + ARP00035	U5842-RL-TG-200-5T9 U5844-PXL-TG-200-5T9 U5168-XTL-200-5T9 U5842-RL-TG-200-5T9 U5844-PXL-TG-200-5T9	LG0408B1200RT + H35815-2 LG0816B1200RCT + H35815-2 MM0202B1200 + EMC5J MM0202B1200R + EMC5J MC0816B1200CT + EC5J2	SC12L200S + Breakers + 5J SC2040M200C + Breakers + 5J	M208CR2A + ARP00035MEP R208CR2A + ARP00035MEP R208CR2AETG + ARP00035MEP
300A			U6601-X-TG-2/200-5T9 U6604-X-TG-2/200-5T9	MK0402L1400RLM + (2)QN2200RH + H35815-2		MS45508C + MS5MIL + LUGS RS45500C + MS5MIL + LUGS

\* To provide 100A service, this socket will be installed and a separate Customer supplied 100A breaker will be installed to supply the 100A service.

### Duplex Meter Sockets – Overhead

Service Size	Eaton	Durham	Milbank	Talon	Square D	Eaton B-Line	Midwest
100A	UT2R1121BCH UT2R1421BCH	SBG1012B UT-2R1121B	U5902-X-2/K1 + BREAKERS	UA2311-0G WEPK2211	UT2R1121B	H012 142 MCC 2012 MS60 152 MCCM	UT2R1121BMEP
200A	UT2R2332BCH UT2R2332BCH	UT-2R2332T SBG2022T	U1252-X-HSP-2/K2 U5882-X-2/K2+ BREAKERS	UA2716-0G WEPK421	UT2R2122B	2222 + Lugs 242 MCC	UT2R2332TMEP

\* To provide 100A service, these sockets will be installed with Customer supplied 100A breakers.

\*\* To provide 200A service, these sockets will be installed with Customer supplied 200A breakers.

### Duplex Meter Sockets – Overhead (5th Lug)

Service Size	Eaton	Durham	Milbank	Talon	Square D	Eaton B-Line	Midwest
100A	UGT2R1121BCH  UGT2R1421BCH UT2R1121BCH  UT2R1421BCH	UGT-2R1121B SBG1012B + ARP00035	U5902-X-2/K1-5T9 + Breakers	WSN251CR UA2311-0G + H659-0121  WEPK2211RJ	UT2R1121B + A5J	H012 + 50365 152 MCCM + 50365  2012 MS60 + 50365	UT2R1121BMEP + ARP00035MEP
200A	UGT2R2332BCH  UT2R2332BCH +	UGT-2R2332T  SBG2022T + ARP00035	U1252-X-HSP- 2/K2-5T9 U5882-X-HSP- 2/K2-5T9 + Breakers	UA2716-0G + H659-0121  WEPK4212RJ	UT2R2122B + A5J	2222 + Lugs + 50365  242 MCC + 50365	UT2R2332TMEP + ARP00035MEP

\* To provide 100A service, these sockets will be installed with Customer supplied 100A breakers.

\*\* To provide 200A service, these sockets will be installed with Customer supplied 200A breakers.

### Meter Stacks (3 To 6) – Overhead

SERVICE SIZE	Eaton	Durham	Milbank	Talon	Square D	Eaton B-Line	Midwest
3-100A	UT3R1121BCH	SBG1013B*  UT-3R1121B	U5903-X-2/K2 + Breakers	UA3311-0G  WEPK331		153 MCCM  143 MCC  2013 MS60	UT3R1121BMEP
4-100A	UT4R1121BCH	SBG1014B*  UT-4R1121B	U5904-X-2/K2 + Breakers	UA4311-0G  WEPK4411		H014  144 MCC  154 MCCM	UT4R1121BMEP
5-100A	UT5R1121BCH	SBG1015B*  UT-5R1121B	U5905-X-2/K1 + Breakers	WEPK6511		154 MCCM	UT5R1121BMEP
6-100A	UT6R1131BCH	SBG1016B*  UT-6R1131B	U5906-X-2/K1 + Breakers	WEPK6611			UT6R1131BMEP
3-200A	UT3R2332TCH	SBG2023T  UT-3R2332T	U1253-X-HSP-2/K1  U5883-X-2/K1 + Breakers	UA3717-YG  WEPK4312	UT3R2332T	2223 + lugs  243 MCC	UT3R2332TMEP
4-200A	UT4R2352TCH	SBG2024T  UT-4R2352T	U1254-X-HSP-2/K1  U5884-X-2/K1 + Breakers	UA4719-YG  WEPK4412	UT4R2352T	2224 + lugs  244 MCC	UT4R2352TMEP
5-200A	UT5R2392TTCH	SBG2025UU  UT-5R2392TT	U1255-X-HSP-2/K1  U5885-X-2/K1 + Breakers	UA5719-KG  WEPK6412	UT5R2392TU	245 MCC	UT5R2392TTMEP
6-200A	UT6R2392TTCH	SBG2026U  UT-6R2392TT	U1256-X-HSP-2/K1  U5886-X- 2/K1+Breakers	UA6719-KG  WEPK8612	UT6R2392TU	246 MCC	UT6R2392TTMEP

\* To provide 100A service, these sockets will be installed with Customer supplied 100A breakers.

\*\* To provide 200A service, these sockets will be installed with Customer supplied 200A breakers.

### Meter Stacks (3 To 6) – Overhead (5th Lug)

SERVICE SIZE	Eaton	Durham	Milbank	Talon	Square D	Eaton B-Line	Midwest
3-100A	UGT3R1121BCH  UT3R1121BCH + ARP00035CHJ	UGT-3R1121B	U5903-X-2/K1-5T9 + Breakers	UA3311-0G + 659-0121  WEPK3311RJ		143 MCC + 50365  2013 MS60	UT3R1121BMEP + ARP00035MEP
4-100A	UGT4R1121BCH  UT4R1121BCH + ARP00035CHJ  U4R1121BCRCH	UGT-4R1121B	U5904-X-2/K1-5T9 + Breakers	UA4311-0G + H659-0121  WEPK4411RJ		H014 + 50365  144 MCC + 50365	UT4R1121BMEP + ARP00035MEP
5-100A	UGT5R1121BCH  UT5R1121BCH + ARP00035CHJ  U5R1121BCRCH	UGT-5R1121B	U5905-X-2/K1-5T9+ Breakers	WEPK6511RJ			UT5R1121BMEP + ARP00035MEP
6-100A	UGT6R1131BCH  UT6R1131BCH + ARP00035CHJ	UGT-6R1131B	U5905-X-2/K1-5T9+ Breakers	WEPK6611RJ			UT6R1131BMEP + ARP00035MEP
3-200A	UT3R2332TCH	UGT-3R2332T	U1253-X-HSP-2/K1-5T9  U5883-X-2/K1-5T9 + Breakers	UA3717-YG + H659-0121	UT3R2332T + A5J	243 MCC + 50365  2223 + lugs + 50365	UT3R2332TMEP + ARP00035MEP
4-200A	U4R2352TCRCH	UGT-4R2352T	U1254-X-HSP-2/K1-5T9  U5884-X-2/K1-5T9 + Breakers	UA4719-YG + H659-0121  WEPK6412RJ	UT4R2352T + A5J	244 MCC + 50365  2224 + Lugs + 50365	UT4R2352TMEP + ARP00035MEP
5-200A	UGT5R2392TTCH  UGT5R2392TTCH + ARP00035CHJ	UGT-5R2392TT	U1255-X-HSP-2/K1-5T9  U5885-X-2/K1-5T9 + Breakers	UA5719-KG + H659-0121  WEPK6512	UT5R2392TU + A5J	245 MCC + 50365	UT5R2392TTMEP + ARP00035MEP
6-200A	UGT6R2392TTCH  UT6R2392TTCH + ARP00035CHJ	UGT-6R2392TT	U1256-X-HSP-2/K1-5T9  U5886-X-2/K1-5T9 + Breakers	UA6719-KG + H659-0121  WEPK8612RJ	UT6R2392TU + A5J	246 MCC + 50365	UT6R2392TTMEP + ARP00035MEP

\* To provide 100A service, these sockets will be installed with Customer supplied 100A breakers.

\*\* To provide 200A service, these sockets will be installed with Customer supplied 200A breakers.

### Individual Meter Sockets – Underground

SERVICE SIZE	Eaton	Durham	Milbank	Talon	Square D	Eaton B-Line	Midwest
200A	UTRS212ACH UTRS213ACH UTRS212CCH UTRS213CE URTRS213CEUSCH URTRS213BEUSCH	UT-RS213A UT-RS213C URT-213A URT-213C	U7018-XL-TG U7018-O-TG U7040-O-TG U7040-XL-TG U7043-XL-TG U7043-O-TG	UAT417-PG	UTRS212C UTRS213A URTRS213B + ACP	204	UTRS212CMEP UTRS213CMEP
320A	UTH4330UCH + ARP00429CH + ARP00427CH	UT-H4309U	U4702-X-2/K2	47704-02 + (2)H56732	UTH4330T + ARP00427 + ACPL 1008068		1008836MEP

### Individual Meter Sockets – Underground (5th Lug)

SERVICE SIZE	Eaton	Durham	Milbank	Talon	Midwest
200A	UGTRS223ACH UGTRS213CFLCH	UGT-RS213A UGT-RS213C UGRT-213A UGRT-213C	U7018-XL-TG-5T9 U7018-O-TG-5T9 U7040-O-TG-5T9 U7040-XL-TG - 5T9 U7043-XL-TG-5T9 U7043-O-TG-5T9	UAT417-PG + H659-0121	UGTH4213CMEP UTRS212CMEP + MS5 UTRS213CMEP + MS5
320A		UGT-H4309U	U4702-X-5T9	47704-02 + (2)H56732 + H35815-2	1008836MEP + MS5

### Combination Meter Sockets – Underground

SERVICE SIZE	Eaton	Durham	Milbank	Talon	Eaton B-Line	Midwest
200A	MBT48B200BTS MB816B200BTS	1009051+ TC350	U5168-XTL-200 U5169-XTL-200	MC0816B1200CT	U2M2R	M208CR2A R208CR2A R208CR2AETG
320A		UHC344N3T-C	U6601-X-TG- 2/200 U6604-X-TG- 2/200	MK0402L1400RLM + (2)QN2200RH MK0402L1400SC + (2)QN2200RH	U4042MC	RS45500C RS45524CFMG

### Combination Meter Sockets – Underground (5th Lug)

SERVICE SIZE	Eaton	Durham	Milbank	Talon	Midwest
200A	MB816B200STD	1009051+ TC350 + ARP00035	U5168-XTL-200-5T9 U5169-XTL-200-5T9	MC0816B1200CT + EC5J2	UGTH4213CMEP + MS5
320A		UHC344N3T-C + ARP00035	U6601-X-TG-2/200- 5T9 U6604-X-TG-2/200- 5T9	MK0402L1400RLM + (2)QN2200RH + H35815-2	RS45500C + MS5MIL RS45524CFMG + MS5MIL

## Duplex Meter Sockets – Underground

SERVICE SIZE	Eaton	Durham	Milbank	Talon	Square D	Midwest
2-100A	UT2R1121CCH UT2R1421BCH	UT2R1121A UT-2R1121C SBG1012A*	U5902-X-2/K1+ Breakers	UA2311-0G	UT2R1121B + ACP + A5J	UT2R1121BMEP + ARP00002MEP
2-200A	UT2R2332UCH	UT-2R2332A  SBG2022A SBG2022U	U1252-X-HSP-2/K1  U5882-X-HSP-2/K1 + Breakers	UA2716-XG	UT2R2122B + ACP	UT2R2332TMEP + ARP00016MEP

\* To provide 100A service, these sockets will be installed with Customer supplied 100A breakers.

\*\* To provide 200A service, these sockets will be installed with Customer supplied 200A breakers.

## Duplex Meter Sockets – Underground (5th Lug)

SERVICE SIZE	Eaton	Durham	Milbank	Talon	Square D	Midwest
2-100A	UGT2R1121CCH UGT2R1421BCH UT2R1121CCH + ARP00035CHJ UT2R1421BCH + ARP00035CHJ	UGT2R1121A  UGT-2R1121C SBG1012A + Breakers + ARP00035	U5902-X-2/K1-5T9 + Breakers	UA2311-0G + H659-0121	UT2R1121B + ACP	UT2R1121BMEP + ARP00002MEP + ARP00035MEP
2-200A	UGT2R2332UCH UT2R2332UCH + ARP00035CHJ	UGT-2R2332A  SBG2022A + ARP00035 SBG2022U + ARP00035	U1252-X-HSP-2/K1- 5T9 U5882-X-HSP-2/K1- 5T9 + Breakers	UA2716-XG + H659-0121	UT2R2122B + ACP + A5J	

\* To provide 100A service, these sockets will be installed with Customer supplied 100A breakers.

\*\* To provide 200A service, these sockets will be installed with Customer supplied 200A breakers.

### Meter Stacks (3 To 6) – Underground

SERVICE SIZE	Eaton	Durham	Milbank	Talon	Midwest
3-100A	UT3R1121BCH	UT-3R1121C SBG1013A*	U5903-X-2/K1 + Breakers	UA3311-0G	UT3R1121BMEP + ARP00002MEP
4-100A	UT4R1121CCH	UT-4R1121A UT-4R1121C SBG1014A* SBG1014C*	U5904-X-2/K1 + Breakers	UA4311-0G	UT4R1121BMEP + ARP00002MEP
5-100A	UT5R1121BCH	UT-5R1121C SBG1015A* SBG1015C*	U5905-X-2/K1 + Breakers		UT5R1121BMEP + ARP00002MEP
6-100A	UT6R1131BCH	UT-6R1131C SBG1016A* SBG1016C*	U5906-X-2/K1 + Breakers		UT6R1131BMEP + ARP00002MEP
3-200A	UT3R2332UCH	UT-2R2332U SBG2023A SBG2023U	U1253-X-HSP-2/K1 U5883-X-2/K1 + Breakers	UA3717-ZG	UT3R2332TMEP + ARP00016MEP
4-200A	UT4R2352UFLCH	UT-4R2352A UT-4R2352U SBG2024A SBG2024U	U1254-X-HSP-2/K1 U5884-X-2/K1 + Breakers	UA4719-ZG	UT4R2352TMEP + ARP00016MEP
5-200A	UT5R2392TTCH	UT-5R2392UU SBG2025UU	U1255-X-HSP-2/K1 U5885-X-2/K1+ Breakers	UA5719-MG	UT5R2392TTMEP + (2) ARP00016MEP
6-200A	UT6R2392UUFLCH	UT-6R2392UU SBG2026U	U1256-X-HSP-2/K1 U5886-X-2/K1+ Breakers	UA6719-MG WEPK8612	UT6R2392TTMEP + (2) ARP00016MEP

\* To provide 100A service, these sockets will be installed with Customer supplied 100A breakers.

\*\* To provide 200A service, these sockets will be installed with Customer supplied 200A breakers.

### **Meter Stacks (3 To 6) – Underground (5th Lug)**

SERVICE SIZE	Eaton	Durham	Milbank	Talon	Square D	Midwest
3-100A	UGT3R1121BCH UT3R1121BCH + ARP00035CHJ	UGT-3R1121C SBG1013A + ARP00035	U5903-X-2/K1-5T9+ Breakers	UA3311-0G + 659-0121		UT3R1121BMEP + ARP00002MEP + ARP00035MEP
4-100A	UGT4R1121CCH UT4R1121CCH + ARP00035CHJ	UGT-4R1121A UGT-4R1121C SBG1014A + ARP00035 SBG1014C + ARP00035	U5904-X-2/K1-5T9+ Breakers	UA4311-0G + H659-0121		UT4R1121BMEP + ARP00002MEP + ARP00035MEP
5-100A	UGT5R1121BCH UT5R1121BCH + ARP00035CHJ	UGT-5R1121C SBG1015A + ARP00035 SBG1015C + ARP00035	U5905-X-2/K1-5T9+ Breakers			UT5R1121BMEP + ARP00002MEP + ARP00035MEP
6-100A	UGT6R1131BCH UT6R1131BCH + ARP00035CHJ	UGT-6R1131C SBG1016A + ARP00035 SBG1016C + ARP00035	U5906-X-2/K1-5T9 + Breakers			UT6R1131BMEP + ARP00002MEP + ARP00035MEP
3-200A	UGT3R2332UCH UGT3R2332UCH	UGT-2R2332U SBG2023A + ARP00035 SBG2023U + ARP00035	U1253-X-HSP-2/K1-5T9 U5883-X-2/K1-5T9+ Breakers	UA3717-ZG + H659-0121	UT3R2332T + A5J + ACPL	UT3R2332TMEP + ARP00016MEP + ARP00035MEP
4-200A	UGT4R2352UFLCH UT4R2352UFLCH + ARP00035CHJ	UGT-4R2352A UGT-4R2352U SBG2024A + ARP00035 SBG2024U + ARP00035	U1254-X-HSP-2/K1-5T9 U5884-X-2/K1-5T9 + Breakers	UA4719-ZG + H659-0121	UT4R2352T + A5J + ACPL	UT4R2352TMEP + ARP00016MEP + ARP00035MEP
5-200A	UGT5R2392TTCH UT5R2392TTCH + ARP00035CHJ	UGT-5R2392UU SBG2025UU + ARP00035	U1255-X-HSP-2/K1 U5885-X-2/K1-5T9 + Breakers	UA5719-MG + H659-0121	UT5R2392TU + A5J + ACPL	UT5R2392TTMEP + (2) ARP00016MEP + ARP00035MEP
6-200A	UGT6R2392UUFLCH UT6R2392UUFLCH + ARP00035CHJ	UGT-6R2392UU SBG2026U + ARP00035	U1256-X-HSP-2/K1-5T9 U5886-X-5T9 + Breakers	UA6719-MG + H659-0121	UT6R2392TU + A5J + ACPL	UT6R2392TTMEP + (2) ARP00016MEP + ARP00035MEP

\* To provide 100A service, these sockets will be installed with Customer supplied 100A breakers.

\*\* To provide 200A service, these sockets will be installed with Customer supplied 200A breakers.



## CT/Connection Cabinet

SERVICE SIZE	MILBANK CATALOG #	TALON/SIEMENS CATALOG #	DURHAM CATALOG #
600A TO 800A	363616-CT3R-WB	LG163636CTS1	363616-DDW

## Intersystem Bonding Termination Bar



MANUFACTURER	CATALOG #
ARLINGTON	GBB50 (#6-1/0)



MANUFACTURER	CATALOG #
EATON	MSEGR2 (#8-1/0)

## Grounding Clamps



CONDUIT SIZE	TAP CONDUCTOR RANGE	MANUFACTURER	CATALOG #
1/2" – 1"	#10 SOL – #2 STR	PENN-UNION	KP-1
			KP-1-DB
		BURNDY	C-11N
			C-11D
		NSI INDUSTRIES	G-1-S
			G-1
		ERICO	CWP1JSH
			CWP1JU
		HARGER	BGC4
		THOMAS & BETTS	J
JD			
1-1/4" – 2"	#10 SOL – #2 STR	PENN-UNION	KP-2
			KP-2-DB
		BURNDY	C-22
			C-22D
		NSI INDUSTRIES	G-2-S
			G-2
		ERICO	CWP2JSH
			CWP2JU
		HARGER	BGC41.25-2
		THOMAS & BETTS	J2BB
J2D			
2-1/2" – 4"	#10 SOL – #2 STR	PENN-UNION	KP-4
		BURNDY	C-4
		NSI INDUSTRIES	G-4-S
			G-4
			G-4-SBS
		HARGER	BGC42.5-4
4-1/2" – 6"	#10 SOL – #2 STR	PENN-UNION	KP-6
		BURNDY	C-8
		NSI INDUSTRIES	G-6-S
			G-6

## **Appendix B**

Excerpts from the NEC are placed here for your convenience. For more detail information, please consult the NEC directly.

### **Part VI. Service Equipment — Disconnecting Means**

**230.70 General.** Means shall be provided to disconnect all ungrounded conductors in a building or other structure from the service conductors.

**(A) Location.** The service disconnecting means shall be installed in accordance with 230.70(A)(1), (A)(2), and (A)(3).

**(1) Readily Accessible Location.** The service disconnecting means shall be installed at a readily accessible location either outside of a building\* or structure or inside nearest the point of entrance of the service conductors.

**(2) Bathrooms.** Service disconnecting means shall not be installed in bathrooms.

**(3) Remote Control.** Where a remote control device(s) is used to actuate the service disconnecting means, the service disconnecting means shall be located in accordance with 230.70(A)(1).

**(B) Marking.** Each service disconnect shall be permanently marked to identify it as a service disconnect.

**(C) Suitable for Use.** Each service disconnecting means shall be suitable for the prevailing conditions. Service equipment installed in hazardous (classified) locations shall comply with the hazardous location requirements.

\* Liberty requires an external disconnect.

#### **230.71 Maximum Number of Disconnects.**

Each service shall have only one disconnecting means unless the requirements of 230.71(B) are met.

**(A) General.** For the purpose of this section, disconnecting means installed as part of listed equipment and used solely for the following shall not be considered a service disconnecting means:

- (1) Power monitoring equipment
- (2) Surge-protective device(s)
- (3) Control circuit of the ground-fault protection system
- (4) Power-operable service disconnecting means

#### **(B) Two to Six Service Disconnecting Means.**

Two to six service disconnects shall be permitted for each service permitted by 230.2 or for each set of service-entrance conductors permitted by 230.40, Exception No. 1, 3, 4, or 5. The two to six service disconnecting means shall be permitted to consist of a combination of any of the following:

- (1)** Separate enclosures with a main service disconnecting means in each enclosure
- (2)** Panelboards with a main service disconnecting means in each panelboard enclosure
- (3)** Switchboard(s) where there is only one service disconnect in each separate vertical section with barriers provided between each vertical section to maintain the inadvertent contact protection required in 230.62 based on access from the adjacent section(s) Service disconnects in switchgear, transfer switches, or metering centers where each disconnect is located in a separate compartment.
- (4)** Metering centers with a main service disconnecting means in each metering center
- (5)** Motor control center(s) where there is only one service disconnect in a motor control center unit and a maximum of two service disconnects provided in a single motor control center with barriers provided between each motor control center unit or compartment containing a service disconnect to maintain the inadvertent contact protection required in 230.62 based on access from adjacent motor control center unit(s) or compartment(s)

**Table 250.66 Grounding Electrode Conductor for Alternating-Current Systems**

Size Of Largest Ungrounded Conductor or Equivalent Area for Parallel Conductors (AWG/kcmil)		Size Of Grounding Electrode Conductor (AWG/kcmil)	
Copper	Aluminum or Copper-Clad Aluminum	Copper	Aluminum or Copper-Clad Aluminum
2 or smaller	1/0 or smaller	8	6
1 or 1/0	2/0 or 3/0	6	4
2/0 or 3/0	4/0 or 250	4	2
Over 3/0 through 350	Over 250 through 500	2	1/0
Over 350 through 600	Over 500 through 900	1/0	3/0
Over 600 through 1100	Over 900 through 1750	2/0	4/0
Over 1100	Over 1750	3/0	250

Notes:

1. If multiple sets of service-entrance conductors connect directly to a service drop, set of overhead service conductors, set of underground service conductors, or service lateral, the equivalent size of the largest service-entrance conductor shall be determined by the largest sum of the areas of the corresponding conductors of each set.
2. If there are no service-entrance conductors, the grounding electrode size shall be determined by the equivalent size of the largest service-entrance conductor required for the load to be served.
3. See installation restrictions in 250.64.

**Table 310.15(C)(1) Adjustment Factors for More Than Three Current-Carrying Conductors**

Number of Conductors*	Percent of Values in Table 310.16 Through Table 310.19 as Adjusted for Ambient Temperature if Necessary
4-6	80
7-9	70
10-20	50
21-30	45
31-40	40
41 and above	35

\* Number of conductors is the total number of conductors in the raceway or cable, including spare conductors. The count shall be adjusted in accordance with 310.15 (E) and (F). The count shall not include conductors that are connected to electrical components that cannot be simultaneously energized.

**Table 310.16 Ampacities of Insulated Conductors with Not More Than Three Current-Carrying Conductors in Raceway, Cable, or Earth (Directly Buried)**

Temperature Rating of Conductor [See NEC Table 310.4(1)]							
Size AWG or kcmil	60°C (140°F)	75°C (167°F)	90°C (194°F)	60°C (140°F)	75°C (167°F)	90°C (194°F)	Size AWG or kcmil
	Types TW, UF	Types RHW, THHW, THW, THWN, XHHW, XHWN, USE, ZW	Types TBS, SA, SIS, FEP, FEPB, MI, PFA, RHH, RHW-2, THHN, THHW, THW-2, THWN-2, USE-2, XHH, XHHW, XHHW-2, XHWN, XHWN-2, XHHN, Z, ZW-2	Types TW, UF	Types RHW, THHW, THW, THWN, XHHW, XHWN, USE	Types TBS, SA, SIS, THHN, THHW, THW-2, THWN-2, RHH, RHW-2, USE-2, XHH, XHHW, XHHW-2, XHWN, XHWN-2, XHHN	
	COPPER			ALUMINUM OR COPPER-CLAD ALUMINUM			
18**	—	—	14	—	—	—	—
16**	—	—	18	—	—	—	—
14**	15	20	25	—	—	—	—
12**	20	25	30	15	20	25	12**
10**	30	35	40	25	30	35	10**
8	40	50	55	35	40	45	8
6	55	65	75	40	50	55	6
4	70	85	95	55	65	75	4
3	85	100	115	65	75	85	3
2	95	115	130	75	90	100	2
1	110	130	145	85	100	115	1
1/0	125	150	170	100	120	135	1/0
2/0	145	175	195	115	135	150	2/0
3/0	165	200	225	130	155	175	3/0
4/0	195	230	260	150	180	205	4/0
250	215	255	290	170	205	230	250
300	240	285	320	195	230	260	300
350	260	310	350	210	250	280	350
400	280	335	380	225	270	305	400
500	320	380	430	260	310	350	500
600	350	420	475	285	340	385	600
700	385	460	520	315	375	425	700
750	400	475	535	320	385	435	750
800	410	490	555	330	395	445	800
900	435	520	585	355	425	480	900
1000	455	545	615	375	445	500	1000
1250	495	590	665	405	485	545	1250
1500	525	625	705	435	520	585	1500
1750	545	650	735	455	545	615	1750
2000	555	665	750	470	560	630	2000

Notes:

- Section 310.15(B) shall be referenced for ampacity correction factors where the ambient temperature is other than 30°C (86°F).
- Section 310.15(C)(1) shall be reference for more than three current-carrying conductors.
- Section 310.16 shall be referenced for conditions of use.

\* Section 240.4(D) shall be referenced for conductor overcurrent protection limitations, except as modified elsewhere in the Code.



## **Most Common Reasons for Delays in Service Connection**

- **CUSTOMER HAS NOT APPLIED FOR SERVICE**
- **THE SERVICE PATH WAS NOT CLEAR**
- **METER SOCKET WAS NOT GROUNDED**
- **NO GROUND ROD OR IMPROPER GROUND ROD**
- **METER SOCKET WAS EITHER TOO HIGH OR LOW**
- **METER SOCKET WAS NOT PROPERLY ATTACHED**
- **METER SOCKET WAS IMPROPERLY WIRED**
- **METER SOCKET WAS NOT APPROVED BY COMPANY**
- **WEATHERHEAD WAS TOO LOW**
- **NO SERVICE ATTACHMENT POINT OR BRACKET**
- **SERVICE ATTACHMENT POINT WAS TOO LOW**
- **WRONG SIZE OR TYPE OF CONDUIT (WATER PIPE IS NOT ALLOWED)**
- **NO STRAPS ON THE CONDUIT**
- **TRENCH WAS TOO SHALLOW**
- **TRENCH PATH WAS NOT LINE OF SIGHT**
- **WRONG GROUND WIRE SIZE**
- **GROUND WIRE WAS NOT ATTACHED**
- **NO PROTECTIVE BUSHINGS ON THE CONDUITS**
- **CONDUIT WAS NOT PROPERLY SUPPORTED IN THE BOTTOM OF THE TRENCH**
- **LOCAL INSPECTION NOT OBTAINED (AS REQUIRED)**
- **MULTIPLE SOCKETS/SERVICES WERE NOT LABELED CORRECTLY**
- **CONSTRUCTION FEES NOT PAID**